

THE MANGA GUIDE™ TO

COMICS
INSIDE!

ELECTRICITY

KAZUHIRO FUJITAKI
MATSUDA
TREND-PRO CO., LTD.



VISIT...

LANZAROTE
Caliente.COM

PRAISE FOR THE MANGA GUIDE SERIES

"I love, love, love this idea! EduManga is a great concept."

—THE OTAKU LIBRARIAN

"These books will make studying fun for teens."

—CONNECTINGWITHYOURTEENS.BLOGSPOT.COM

"The art is nicely clean and filled with just the right amount of detail, and the characters are quite expressive and given to funny asides."

—WARREN PEACE

"This is a perfect addition to a home school curriculum."

—PARENTING SQUAD

"The series' shoujo style and spunky schoolgirl heroines make the books a good potential fit for those manga readers who've made *Fruits Basket* a hit."

—BLOGCRITICS.ORG

PRAISE FOR THE MANGA GUIDE TO STATISTICS

"This is really what a good math text should be like. Unlike the majority of books on subjects like statistics, it doesn't just present the material as a dry series of pointless-seeming formulas. It presents statistics as something fun, and something enlightening."

—GOOD MATH, BAD MATH

"*The Manga Guide to Statistics* is a solid introduction to the world of statistical analysis done in a fun and accessible way."

—ACTIVE ANIME

"Inoue's art is clean, cute and simplified, and it works with machine-like efficiency—the artist not only knows and speaks the language of manga, but does so fluently."

—NEWSARAMA

"For those who've been taking math classes in high school or college, I think this book will be very helpful in making statistics easier to understand."

—ASTRONERDBOY'S ANIME & MANGA BLOG

"This book is an excellent introductory book on statistics."


—GOLDEN TRIANGLE PC CLUB

"This manga succeeds in presenting important statistical concepts in an accessible and entertaining way. The charm of the book lies in the real-world examples it uses."

—CURLLED UP WITH A GOOD BOOK



THE MANGA GUIDE™ TO ELECTRICITY



THE MANGA GUIDE™ TO
ELECTRICITY

KAZUHIRO FUJITAKI
MATSUDA
TREND-PRO CO., LTD.



THE MANGA GUIDE TO ELECTRICITY. Copyright © 2009 by Kazuhiro Fujitaki and TREND-PRO Co., Ltd.

The Manga Guide to Electricity is a translation of the Japanese original, *Manga de Wakaru Denki*, published by Ohmsha, Ltd. of Tokyo, Japan, © 2006 by Kazuhiro Fujitaki and TREND-PRO Co., Ltd.

This English edition is co-published by No Starch Press, Inc. and Ohmsha, Ltd.

All rights reserved. No part of this work may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying, recording, or by any information storage or retrieval system, without the prior written permission of the copyright owner and the publisher.

13 12 11 10 09 2 3 4 5 6 7 8 9

ISBN-10: 1-59327-197-2

ISBN-13: 978-1-59327-197-8

Publisher: William Pollock

Author: Kazuhiro Fujitaki

Illustrator: Matsuda

Producer: TREND-PRO Co., Ltd.

Production Editor: Megan Dunchak

Developmental Editor: Tyler Ortman

Translator: Arnie Rusoff

Technical Reviewers: Dave Issadore and Keith Brown

Compositor: Riley Hoffman

Proofreader: Cristina Chan

Indexer: Sarah Schott

For information on book distributors or translations, please contact No Starch Press, Inc. directly:
No Starch Press, Inc.

555 De Haro Street, Suite 250, San Francisco, CA 94107

phone: 415.863.9900; fax: 415.863.9950; info@nostarch.com; <http://www.nostarch.com/>

Library of Congress Cataloging-in-Publication Data

Fujitaki, Kazuhiro.

[Manga de waku denki. English]

The manga guide to electricity / Kazuhiro Fujitaki, Matsuda, and Trend-pro Co., Ltd.

p. cm.

Includes index.

ISBN-13: 978-1-59327-197-8

ISBN-10: 1-59327-197-2

1. Electricity--Comic books, strips, etc. 2. Electricity--Popular works. I. Trend-pro Co. II. Title.

QC527.F8513 2009

537--dc22

2008054602

No Starch Press and the No Starch Press logo are registered trademarks of No Starch Press, Inc. Other product and company names mentioned herein may be the trademarks of their respective owners. Rather than use a trademark symbol with every occurrence of a trademarked name, we are using the names only in an editorial fashion and to the benefit of the trademark owner, with no intention of infringement of the trademark.

The information in this book is distributed on an "As Is" basis, without warranty. While every precaution has been taken in the preparation of this work, neither the author nor No Starch Press, Inc. shall have any liability to any person or entity with respect to any loss or damage caused or alleged to be caused directly or indirectly by the information contained in it.

All characters in this publication are fictitious, and any resemblance to real persons, living or dead, is purely coincidental.

CONTENTS

PREFACE.....	xi
--------------	----

PROLOGUE

FROM ELECTOPIA, THE LAND OF ELECTRICITY.....	1
--	---

1

WHAT IS ELECTRICITY?.....	13
---------------------------	----

Electricity and Everyday Life.....	14
Electrical Units.....	15
Electricity in the Home.....	19
How Electricity Works.....	25
The True Nature of Electricity.....	26
Current and Electrical Discharge.....	30
Atomic Structure and Conductivity.....	34
Static Electricity.....	36
The Triboelectric Series.....	40
Uses of Static Electricity.....	43
Tags on Consumer Electric Products.....	45
Voltage and Potential.....	46
Atoms and Electrons.....	47
Static Electricity.....	49
Electrostatic Force.....	49
The Triboelectric Series.....	51
Movement of Charge and Direction of Current.....	51

2

WHAT ARE ELECTRIC CIRCUITS?.....	55
----------------------------------	----

Electric Circuits in Everyday Devices.....	56
A Flashlight's Circuit.....	59
Parts of an Electric Circuit.....	61
Ohm's Law and Methods of Connecting Electrical Components.....	67
Electric Circuits and Ohm's Law.....	68
Series and Parallel Connections.....	69
Electric Circuits and Current.....	73
Graphical Symbols.....	73
Direct Current Circuit and Alternating Current Circuit.....	74
Ohm's Law.....	76
Resistivity and Conductivity.....	77
Effective Resistance.....	78

3

HOW DOES ELECTRICITY WORK?..... 81

Why Does Electricity Produce Heat?	82
Electricity and Joule Heat	85
How Is Heat Generated by Current?	87
Thermal Emission and Luminescence	90
Current and Magnetic Fields.	94
Fleming's Left-Hand Rule (For DC Motors).	98
Fleming's Right-Hand Rule (For Generators)	100
Joule Heat.	104
Thermal Vibration.	104
Electromagnetic Waves.	106
Electricity and Magnetism	107
Fleming's Left-Hand Rule and Motors	109
Fleming's Right-Hand Rule and Electric Generators	110
Electricity and Coils.	111
Coils and Electromagnetic Induction.	111
Coils and Inductance.	112
Coils and Alternating Current	113
Coils and Transformers	114
Capacitors	115
Capacitors and Alternating Current.	115

4

HOW DO YOU CREATE ELECTRICITY?..... 117

Generators	118
How Does a Power Generator Create Electricity?	121
Batteries and Other Sources of Electricity	124
Chemical Cells	126
What Happens in a Dry Cell Battery?	132
Water and Fuel Cells	135
Anodes and Cathodes	138
Creating Your Own Coin Battery	140
Thermopiles	141
Electricity Created by a Power Plant	147
Thermal Power Generation.	149
Nuclear Power Generation	151
Hydroelectric Power Generation.	152
Wind Power Generation	154

HOW CAN YOU CONVENIENTLY USE ELECTRICITY?	155
What Are Semiconductors?	161
Diodes and Transistors	169
Diodes That Emit Light	174
Transistors	176
Diodes	186
Transistors	188
Field-Effect Transistor	188
Converters and Inverters	189
Sensors	190
Temperature Sensors	190
Optical Sensors	192
EPILOGUE	197
INDEX	201

PREFACE

Our current lifestyle necessitates the use of electricity. Electric current is often explained by comparing it to flowing water, but since electricity cannot be seen by the naked eye, this metaphor can be difficult to understand. What can we do to better understand electricity?

Electricity is very helpful in almost every facet of our lives; it produces light, heat, and power. Even though we can see these benefits, we are usually unaware of electricity itself. However, if we simply learn the basics, we can get a clear picture of how electricity works.

This book explains fundamental electrical concepts using a story told through manga followed by further explanations in written text. There are no complicated explanations—readers simply listen along with the heroine Rereko as her teacher Hikaru explains concepts. Even people who have had a hard time understanding electricity will find Hikaru's explanations easy to comprehend.



I am extremely grateful to Matsuda, who provided the artwork, and to everyone at TREND-PRO, who produced the book. I would also like to give my sincere thanks to Professor Masaaki Mitani for checking my work. I am also very thankful to Ohmsha, Ltd. for giving me the opportunity to write this book.



I hope that in reading this book you will learn about electricity and gain a familiarity with it.




KAZUHIRO FUJITAKI
DECEMBER 2006




PROLOGUE:
FROM ELECTOPIA,
THE LAND OF ELECTRICITY


































...AT HIKARU'S APARTMENT





...SO THAT'S WHAT
HAPPENED.

YOU CAME
HERE TO STUDY
FROM ANOTHER
WORLD.

ELECTOPIA IS A LAND
IN WHICH ELECTRICITY
IS A LITTLE MORE
ADVANCED THAN IT IS
IN THIS WORLD.

SINCE THE STUDY OF
ELECTRICITY IS THOUGHT
TO BE SO IMPORTANT,
EVEN KIDS IN MY GRADE
MUST KNOW THE BASICS.
BUT ACTUALLY, I'M...
WHAT CAN I SAY? I'M...




A LOSER!!



$\mathbb{E} = \mathbb{E}, \mathbb{E} =$
 $\mathbb{E} = \mathbb{E}, \mathbb{E} =$

FWAR

SO, BY TAKING
EXTRA CLASSES
HERE, YOU'LL TRY
TO MAKE UP FOR
THE AMOUNT YOU'VE
FALLEN BEHIND?

TETKA SENSEI IS VERY KNOWLEDGEABLE ABOUT THIS WORLD.














1


WHAT IS ELECTRICITY?



ELECTRICITY AND EVERYDAY LIFE









VOLTAGE IS THE DIFFERENCE IN POTENTIAL BETWEEN TWO POINTS.

DIFFERENCE IN WATER LEVEL =
DIFFERENCE IN POTENTIAL =
VOLTAGE

ON THE OTHER HAND,
A (AMPERE OR AMP
FOR SHORT) IS THE
UNIT REPRESENTING
ELECTRIC CURRENT.




A





CURRENT IS THE AMOUNT OF ELECTRICITY FLOWING PER SECOND THROUGH AN ELECTRIC LINE. IN TERMS OF WATER, THIS WOULD BE THE WATER VOLUME PER SECOND.






THIS MAKES
ME WANT TO
EAT NAGASHI
SOMEN – FLOWING
NOODLES!










A DISTRIBUTION BOARD DIVIDES ELECTRICITY FOR EACH ROOM IN THE HOUSE. THE ELECTRICITY THAT ENTERS THE DISTRIBUTION BOARD



PASSES THROUGH A CURRENT LIMITER, ENTERS A LEAKAGE CIRCUIT BREAKER, AND IS DIVIDED AMONG MULTIPLE SAFETY BREAKERS.

LEAKAGE CIRCUIT BREAKER

CURRENT LIMITER

SAFETY BREAKERS

THE INSIDE OF A DISTRIBUTION BOARD LOOKS LIKE THIS.


HUH.

IF THE TOTAL CURRENT FLOWING THROUGH MULTIPLE SAFETY BREAKERS EXCEEDS THE MAXIMUM CURRENT VALUE, THE CURRENT LIMITER WILL TRIP.

IN MY HOUSE, THE MAXIMUM CURRENT VALUE ALLOWED IS 20A.

SO IF THE CURRENT IS MORE THAN 20A, IT WILL TRIP FOR SAFETY, RIGHT?

THESE ARE THE SAFETY BREAKERS!



IF A CURRENT OF 20A OR MORE IS FLOWING, THIS WILL TRIP FOR SAFETY.

SO, IF THE TOTAL ELECTRICITY USED BY THE ELECTRONIC APPLIANCES CONNECTED TO ONE SAFETY BREAKER DOES NOT EXCEED 20A...

SINCE THE VOLTAGE OF A HOUSEHOLD ELECTRICAL OUTLET IS ALWAYS 120V, LET'S TRY CALCULATING THE TOTAL POWER USED BY THE APPLIANCES CONNECTED TO ONE SAFETY BREAKER AND SEE IF IT EXCEEDS THE LIMIT.

FOR EXAMPLE, IF WE TRY USING THE ELECTRIC KETTLE AND THE RICE COOKER...



ELECTRIC TEA KETTLE
 $840W / 120V = 7.0A$







RICE COOKER
 $1500W / 120V = 12.5A$


$$7.0A + 12.5A = 19.5A$$

...THE SAFETY BREAKER WILL NOT TRIP.

THIS COMBINATION JUST MAKES IT BY A WHISKER...


20A HAS NOT BEEN EXCEEDED.





HOW ELECTRICITY WORKS

AROUND 600 BC, THE GREEK PHILOSOPHER THALES DISCOVERED THAT WHEN AN AMBER ORNAMENT WAS RUBBED WITH A CLOTH, IT ATTRACTED FEATHERS OR PIECES OF LINT.



AH! IS THIS, BY ANY CHANCE...

...DUE TO STATIC ELECTRICITY!?

YEP!

BUT, IN THOSE DAYS, THEY DIDN'T KNOW ABOUT STATIC ELECTRICITY.

INCIDENTALLY, THE WORD *ELECTRICITY* COMES FROM THE WORD *ELECTRON*, WHICH MEANS AMBER IN GREEK.

electron


HUH!

THE MYSTERIOUS FORCE THAT ATTRACTS TINY OBJECTS TOGETHER CAN NOW BE EXPLAINED WITH ELECTRICITY.

?

THE TRUE NATURE OF ELECTRICITY

SO LET'S TRY TO
CLOSE IN ON THE
TRUE NATURE OF
ELECTRICITY!





ACTUALLY, THE
TRUE NATURE OF
ELECTRICITY COMES
FROM TINY THINGS
INSIDE EVERY
SUBSTANCE.

HUH?

EVEN IN YOU
AND ME?




THAT'S RIGHT!
IT'S IN BOTH YOU AND ME.
ALL SUBSTANCES ARE MADE UP OF
COLLECTIONS OF TEENSY LITTLE
PARTICLES CALLED **ATOMS**.



HMM.



NUCLEUS




ELECTRON

AN ATOM HAS
SOMETHING CALLED
A **NUCLEUS** AT ITS
CENTER, AND THINGS
CALLED **ELECTRONS**
REVOLVE AROUND IT.

THESE EVEN TINIER
PARTICLES ARE
THE CAUSE OF
ELECTRICITY.

IF I REMEMBER
CORRECTLY, YOUR
PLANETS ALSO
REVOLVE AROUND
YOUR SUN, RIGHT?



IS IT SIMILAR
TO THAT
RELATIONSHIP?

IT IS! THE NUCLEUS, WHICH CORRESPONDS TO THE SUN, CONSISTS OF PROTONS, WHICH HAVE AN ELECTRICALLY POSITIVE PROPERTY, AND NEUTRONS, WHICH HAVE NO ELECTRICAL PROPERTY.

PROTON
(+)

NEUTRON
(NEUTRAL)

THE ELECTRONS THAT REVOLVE AROUND THE OUTSIDE HAVE A NEGATIVE PROPERTY.

ELECTRON
(-)

IF AN ATOM CONTAINS BOTH POSITIVES AND NEGATIVES, IS THE ATOM ITSELF POSITIVE OR NEGATIVE?

SINCE THE NUMBER OF PROTONS IS USUALLY THE SAME AS THE NUMBER OF ELECTRONS, THE ATOM ITSELF IS ELECTRICALLY NEUTRAL.

NOW, IF EXTERNAL HEAT OR LIGHT IS ADDED TO AN ATOM...

HEAT


LIGHT

ZIP!


YOW!

AN ELECTRON MAY ESCAPE FROM THE ATOM. THIS IS CALLED A FREE ELECTRON.

WHAT HAPPENS IF IT ESCAPES?



IF AN ELECTRON ESCAPES, THE NEGATIVES ARE REDUCED, AND THE ATOM BECOMES ELECTRICALLY POSITIVE.



THE NUMBER OF ELECTRONS DECREASES, AND THE ATOM BECOMES ELECTRICALLY POSITIVE.

HEAT

LIGHT

THE NUMBER OF ELECTRONS INCREASES, AND THE ATOM BECOMES ELECTRICALLY NEGATIVE.

IF AN ESCAPED ELECTRON PLUNGES INTO ANOTHER ATOM, THE NEGATIVES IN THAT ATOM INCREASE, AND IT BECOMES ELECTRICALLY NEGATIVE.



AHA! THE ESCAPED ELECTRON MOVES TO ANOTHER ATOM!

AN ATOM THAT HAS THIS KIND OF ELECTRICAL PROPERTY IS SAID TO BE CHARGED.


SO AN ATOM IS CHARGED WHEN ONE OF ITS ELECTRONS ESCAPES OR WHEN IT RECEIVES ANOTHER ELECTRON.



CHARGE IS THE POSITIVE OR NEGATIVE ELECTRICAL PROPERTY. A PROTON IS SAID TO HAVE POSITIVE CHARGE AND AN ELECTRON NEGATIVE CHARGE.

CHARGE...??

TWO POSITIVE CHARGES OR TWO NEGATIVE CHARGES REPEL EACH OTHER, WHILE A POSITIVE AND A NEGATIVE ATTRACT EACH OTHER.



IT'S LIKE THE NORTH AND SOUTH POLES OF A MAGNET, ISN'T IT?

YEP! THIS FORCE IS CALLED THE **ELECTROSTATIC FORCE** OR **COULOMB'S FORCE**.

STATIC ELECTRICITY OCCURS WHEN A MATERIAL HAS A POSITIVE OR NEGATIVE ELECTRIC CHARGE THAT IS NOT MOVING.

CURRENT AND ELECTRICAL DISCHARGE

IF A SUBSTANCE IS POSITIVELY OR NEGATIVELY CHARGED, IT TRIES TO BECOME NEUTRAL AGAIN BY RECEIVING OR LOSING ELECTRONS.

IT TRIES TO GET BACK TO ITS NATURAL STATE, DOESN'T IT?

BY THE WAY, OBJECTS CAN BE *CONDUCTORS*, THROUGH WHICH ELECTRICITY EASILY FLOWS (LIKE METAL)...

...*INSULATORS*, THROUGH WHICH ELECTRICITY HAS DIFFICULTY FLOWING (LIKE GLASS OR RUBBER)...





...AND *SEMICONDUCTORS*, WHICH ARE MIDWAY BETWEEN CONDUCTORS AND INSULATORS.

HMMM.


IF THERE IS AN INSULATOR BETWEEN A POSITIVE AND A NEGATIVE CHARGE, THE ELECTRONS CANNOT MOVE.

INSULATOR

BECAUSE THE ELECTRICITY HAS DIFFICULTY FLOWING, RIGHT?




THIS IS WHAT LIGHTNING IS!
LIGHTNING OCCURS WHEN TINY
WATER DROPLETS IN CLOUDS
RUB AGAINST EACH OTHER, AND
THE STATIC ELECTRICITY THAT
WAS PRODUCED DISCHARGES
TO THE GROUND.




HAIL AND ICE PARTICLES IN
CUMULONIMBUS CLOUDS
COLLIDE WITH EACH OTHER,
AND ELECTRIC CHARGE
ACCUMULATES.


SINCE AIR IS AN
INSULATOR, A
DISCHARGE DOES
NOT OCCUR EASILY.



THEN AN
ENORMOUS
DISCHARGE
OCCURS!



AN ELECTRICAL DISCHARGE
OCCURS, EITHER WITHIN THE
CLOUD ITSELF OR IN THE
FORM OF LIGHTNING TO
THE GROUND.






WHEN A LARGE AMOUNT
OF CHARGE BUILDS UP,
AND THERE IS A
DIFFERENCE IN POTENTIAL
BETWEEN THE POSITIVE
AND NEGATIVE CHARGES...
OR, IN OTHER WORDS,
WHEN THE VOLTAGE
BECOMES VERY HIGH...

THE BREAKDOWN
OF THE INSULATION
CREATES AWESOME
POWER, RIGHT?

THE INSULATION OF THE
AIR SUDDENLY BREAKS
DOWN, AND AN ELECTRICAL
DISCHARGE OCCURS.

IT DOES!
BUT IT HAPPENS
IN AN INSTANT.



ATOMIC STRUCTURE AND CONDUCTIVITY

THERE ARE VARIOUS KINDS OF ATOMS, AND A NUMBER IS ASSIGNED TO EACH ONE.

THIS IS CALLED THE ATOMIC NUMBER.


FOR EXAMPLE, THE ATOMIC NUMBER OF COPPER, WHICH IS OFTEN USED IN ELECTRIC LINES, IS 29.

WHY IS COPPER NUMBER 29?




THE ATOMIC NUMBER IS THE SAME AS THE NUMBER OF PROTONS THAT THE ATOM HAS.

AND SINCE THERE ARE THE SAME NUMBER OF PROTONS AS ELECTRONS, COPPER MUST ALSO HAVE 29 ELECTRONS.

THERE ARE FOUR ORBITS CALLED ELECTRON SHELLS AROUND THE NUCLEUS OF A COPPER ATOM. STARTING FROM THE INNERMOST SHELL, THESE CONTAIN 2, 8, 18, AND 1 ELECTRON, RESPECTIVELY, FOR A TOTAL OF 29 ELECTRONS.



AN ELECTRON IN THE OUTERMOST SHELL IS CALLED A VALENCE ELECTRON.



STATIC ELECTRICITY

EARLIER I TOLD YOU THAT STATIC ELECTRICITY OCCURS WHEN AN OBJECT HAS AN ELECTRICALLY POSITIVE OR NEGATIVE CHARGE. *STATIC* MEANS THAT NOTHING IS MOVING—NO CURRENT FLOWS.

NOW LET'S TALK ABOUT STATIC ELECTRICITY IN A LITTLE MORE DETAIL.

OKAY!

YOU KNOW, WE ALSO HAVE FOUR SEASONS IN ELECTOPIA, AND IN WINTER, IT SEEMS TO CAUSE LITTLE SHOCKS EVERYWHERE... IT'S JUST AWFUL.

ZAP

WITH SWEATERS

ZAP

OW!

OW!

ZAP




WITH DOOR KNOBS



WELL, IN THAT SENSE, STATIC ELECTRICITY IS SOMETHING WE'RE RELATIVELY FAMILIAR WITH. BUT DO YOU KNOW HOW IT IS PRODUCED AND WHAT PROPERTIES IT HAS?




WELL...




UM...IT'S...






THAT'S WHAT I THOUGHT!



























TAGS ON CONSUMER ELECTRIC PRODUCTS

Consumer electric products have tags related to electricity with information such as voltage, current, and power—for example, 120V, 1440W, and 12A.



A tag on an electric heater

Voltage, the potential difference or “pressure” that makes electricity flow, is represented by the symbol V . The unit used to measure voltage is the *volt* (V), which is named for the Italian physicist Alessandro Volta, who invented the battery. The voltage used in an ordinary household appliance is 120V in the United States, 240V in Europe, and 100V in Japan.

Current is the quantity of electricity flowing per second through an electric line, and it is represented using the symbol I , which comes from the initial letter of *Intensity of electricity*. Current is measured in *amperes* (A), or *amps* for short, which are named for the French physicist André Marie Ampère. One amp is equal to one coulomb per second.

Power, which is the electric energy consumed in one second when current flows, is represented using the symbol P . Power is measured in *watts* (W), which are named for the British mechanical engineer James Watt, who invented the steam engine. One watt is equal to one joule per second.

You can determine the power a device draws by multiplying its voltage and current. The power of a 120V device in which 12A of current flows is $P = V \times I = 120V \times 12A = 1440W$.

A typical American household contains many 120V devices. If you divide the power value that is displayed on each of these devices by 120V, you can find the value of the current that flows in each device. For devices with the same power, a 240V electronic device runs using half the current of an 120V electronic device.

Since $P = V \times I$, we can rearrange this equation to look like this using simple algebra.

$$I = \frac{P}{V}$$

$$\text{For a 120V electric device... } I = \frac{1440W}{120V} = 12A \quad \dots 12A \text{ of current flows.}$$

$$\text{For a 240V electric device... } I = \frac{1440W}{240V} = 6A \quad \dots 6A \text{ of current flows.}$$

SI PREFIXES

1000W may also be represented by 1kW. This is because *k* stands for *kilo* and represents 1,000 or 10^3 . But we can use other prefixes, too: 3,600,000 joules (J) are equal to 3.6 megajoules (MJ). These prefixes for different powers of 10 are called *SI prefixes*, and they come from internationally determined rules for units called the *International System of Units (SI units)*. The most common ones are shown in the table below.

SI PREFIXES OFTEN USED IN ELECTRICAL RELATIONSHIPS

Prefix Symbol	Name	Quantity
T	tera	10^{12} = 1,000,000,000,000
G	giga	10^9 = 1,000,000,000
M	mega	10^6 = 1,000,000
k	kilo	10^3 = 1,000
m	milli	10^{-3} = 0.001
μ	micro	10^{-6} = 0.000 001
n	nano	10^{-9} = 0.000 000 001
p	pico	10^{-12} = 0.000 000 000 001


You can find the amount of *energy*, which is the total amount of *work* done by an electrical device, by multiplying the power it draws and the time the device operates. Power is often measured by power companies in kWh (kilowatt hours). For example, if an electric heater with 1kW is used for 1 hour, the amount of energy it uses is $1\text{kW} \times 1 \text{ hour} = 1\text{kWh}$.

However, when time is represented in seconds, Ws (watt second) can be used for the energy's unit. A watt-second is equivalent to a *joule (J)*. For example, when a 1kW electric heater is used for 1 hour, since $1 \text{ hour} = 60 \text{ minutes} \times 60 \text{ seconds} = 3600 \text{ seconds}$, the amount of energy used is $1\text{kW} \times 3600 \text{ seconds} = 3600\text{kWs}$ or 3,600,000 joules.

You can calculate how much it will cost to use an ordinary household appliance by multiplying the amount of energy used (in kWh) by the utility company's price per kWh (you will also need to add in any flat-rate charges, if your utility company has them). Since the average electrical utility charge for 1kWh in the United States is approximately 12 cents for 1kWh, if a device with 1kW of power is used for 1 hour, the amount of energy used is 1kWh, and the electrical utility charge will be approximately 12 cents.

VOLTAGE AND POTENTIAL


Electricity flows from a high potential to a low potential. The potential difference between two points is called *voltage*. For example, for a AA battery, if we let the negative pole be the reference point, then the potential of the negative pole is 0V and the potential of the positive pole is 1.5V. The potential difference between the positive and negative poles is the *supply voltage* of this battery.



Supply voltage of a AA battery

If we stack two batteries and let the reference point be point B, the potential of point A is 1.5V, the potential of point B is 0V, and the potential of point C is -1.5V. The voltage between points A and C can be obtained by subtracting the potential of point C from the potential of point A; the voltage, in this case, is 3V. If we let point C be the reference point, the potential of point C is 0V, the potential of point B is 1.5V, and the potential of point A is 3V. The voltage is still 3V. The voltage is still 3V.

The larger the difference in electrical potential, the larger the voltage.




The voltage when two batteries are stacked


ATOMS AND ELECTRONS

All substances are made of atoms. An *atom* consists of a nucleus, which is made of protons and neutrons, and electrons. Since protons have a positive charge and neutrons are electrically neutral, the nucleus itself is electrically positive. Electrons, on the other hand, have a negative charge. But since protons and electrons are equally and oppositely charged, an atom is typically electrically neutral.

Electrons move around the nucleus in a series of orbits called *electron shells*. Since the attraction from the nucleus is weaker for electrons in the outermost shells than ones in the innermost shells, electrons in those outermost shells may escape from orbit if external energy such as heat or light is applied. An electron that has escaped from orbit can move around freely and is called a *free electron*. In substances like copper and other metals,




The smallest quantity of electricity that exists in the natural world is a single electron.



The escape of an electron

through which electricity easily flows, there are many free electrons, and if a voltage is applied to this substance, the free electrons all flow in one direction. This is how electricity flows through an electric line. The outermost electron shell of an atom is called the *valence shell*, and the electrons that are in it are called *valence electrons*.


The total number of electrons in an atom is the same as that atom's atomic number. Although there are many atoms with high atomic numbers and a lot of electrons, those substances are not necessarily ones through which electricity easily flows—the flow of electricity depends on the number of valence electrons.



Different materials have different amounts of free electrons.

STATIC ELECTRICITY

When two different substances are rubbed together, atoms collide, and electrons that are easily separated from the atoms of one substance may escape and move to the atoms of the other substance. At this time, the substance that lost electrons becomes positively charged, and the substance that gained electrons becomes negatively charged. A substance that carries electricity in this way is said to be *charged*, and since this electricity is stationary (that is, it's not flowing), it is called *static electricity*. The quantity of the positive charge that is generated by this process is always the same as the quantity of the negative charge. Since static electricity is generated by friction, it is also called *frictional electricity*.




Electron movement and electric charge

ELECTROSTATIC FORCE

Charge is measured in *coulombs* and is represented by Q , the quantity of charge. The name of the unit comes from Charles Augustine Coulomb, a French physicist who studied electricity.


A force called *electrostatic force* (also known as *Coulomb's force*) operates between two charges. This force causes the same types of charge to repel each other and different types of charge to attract each other. The size of the electrostatic force F of attraction or repulsion (measured in a unit called a newton) operating between charge Q_1 and Q_2 is directly proportional to the product of Q_1 and Q_2 and inversely proportional to the square of the distance (r meters) between the charges. The stronger the charges, and the smaller the distance, the larger the resulting electrostatic force. This is called *Coulomb's law* with respect to static electricity.



Electrostatic force operating between charges and Coulomb's law

If static electricity is generated by rubbing a vinyl sheet on a person's hair, the hair has a positive charge, the vinyl has a negative charge, and the hair clings to the vinyl due to the electrostatic force.

Also, if the negatively charged vinyl sheet is brought close to hair that has not been charged, the hair will become positively charged and will cling to the vinyl. This phenomenon, in which something that is not charged becomes charged when it is in close proximity to something else that is charged, is called *electrostatic induction*.




Electrostatic induction

THE TRIBOELECTRIC SERIES

Static electricity is more easily generated as the air gets drier—humidity prevents static electricity from gathering on a surface. Also, some clothes easily become charged, while others do not, depending on the material they are made from. Since silk has good water absorbency and contains much more moisture than synthetic fibers, it can reduce the occurrence of static electricity.

The polarities of the charges that are generated by friction differ according to the materials that are rubbed together. These differences are represented by the *triboelectric series*. For example, if hair and cotton are rubbed together, the hair will become positively charged and the cotton will become negatively charged, but for cotton and vinyl, the cotton will become positively charged and the vinyl will become negatively charged.



The triboelectric series


The farther apart the materials are in the triboelectric series, the more static electricity is generated between them, and the closer together the objects are in the triboelectric series, the less static electricity is generated. In other words, you can reduce the occurrence of static electricity by wearing clothes that are made of materials that are close together in the triboelectric series.

MOVEMENT OF CHARGE AND DIRECTION OF CURRENT

Lightning is also a result of static electricity. Lightning occurs when the static electricity that is produced by the friction between hail and ice particles in a cloud discharges between the cloud and ground. In the case of lightning, air (which is an insulator through which electricity has difficulty flowing) exists between the positive and negative charges, so a discharge does not easily occur.


When a large amount of charge builds up and the potential difference between the positive and negative charges is extremely large, the insulation of the air suddenly breaks down and an electrical discharge occurs. *Electrical discharge* is the phenomenon in which charge flows continuously. This continuous flow of electricity is called *current*.

Electric current flows from positive to negative. Scientists have discovered that the movement of electrons, however, is from negative to positive. Therefore, the direction in which the electrons move is actually opposite to the direction in which current flows.



Direction of current and direction of electron movement

The amount of current is represented by the quantity of electricity passing through a wire in a second.



Size of the current

For example, when a charge of 1C passes through a given point, the current I can be obtained by dividing the charge (Q) in coulombs by the time (t) in seconds as follows.


$$I = \frac{Q}{t} = \frac{1\text{C}}{1\text{s}} = 1\text{A}$$

Also, the number of electrons flowing at 1A can be obtained by dividing 1C by the quantity of charge in 1 electron, as follows:

$$\frac{1\text{C}}{1.602 \times 10^{-19}\text{C/electron}} = 6.24 \times 10^{18} \text{ electrons}$$

In other words, when a current of 1A is flowing, there are 6.24×10^{18} electrons flowing per second.

The speed at which the electrons move is very slow—less than 1 cm per second. However, the speed at which electrical motion is transmitted to neighboring electrons is the same as the speed of light: 300,000 km per second. Therefore, the current also flows at 300,000 km per second (the speed of light).




Speed of electrons and speed of current

Although electricity itself cannot be seen with the naked eye, heat or light is often produced when current flows. Therefore, we know that electricity exists by observing the phenomena caused by current.









2





WHAT ARE ELECTRIC CIRCUITS?



ELECTRIC CIRCUITS IN
EVERYDAY DEVICES







A FLASHLIGHT'S CIRCUIT

THE INSIDE OF A FLASHLIGHT LOOKS SOMETHING LIKE THIS...

IT'S SO SIMPLE!

A FLASHLIGHT CONSISTS OF ELECTRICAL COMPONENTS CALLED BATTERIES, A MINIATURE LIGHT BULB, AND A SWITCH.




SWITCH

LIGHT BULB

BATTERIES




OKAY...

A BATTERY IS A PRODUCT THAT HAS VOLTAGE (THAT IS, A POTENTIAL DIFFERENCE).




WATER PUMP = BATTERY

IF WE THINK ABOUT IT IN TERMS OF WATER, A BATTERY CORRESPONDS TO A WATER PUMP THAT DRAWS WATER UP OUT OF A WELL.



WHEN THE SWITCH IS CLOSED, CURRENT LEAVES THE POSITIVE POLE OF THE BATTERY, PASSES THROUGH THE MINIATURE BULB AND SWITCH, AND RETURNS TO THE NEGATIVE POLE.



THE PATH THROUGH WHICH THIS CURRENT FLOWS IS CALLED AN *ELECTRIC CIRCUIT*, WHICH ALWAYS HAS A CLOSED FORM (*CLOSED CIRCUIT*).

PARTS OF AN ELECTRIC CIRCUIT







THE VOLTAGE OF THE POWER SUPPLY IS CALLED THE *POWER SUPPLY VOLTAGE* OR *ELECTROMOTIVE FORCE*.





WHEN CURRENT FLOWS, THE *LOAD* CONVERTS ELECTRICAL ENERGY TO LIGHT OR HEAT ENERGY—THAT IS THE WORK THE BATTERY DID ON THE BULB.




I SEE!
IN THE FLASHLIGHT,
THE LIGHT BULB IS THE
LOAD, RIGHT?






THAT'S RIGHT!





THE *LOAD* ALSO HAS A PROPERTY THAT HINDERS THE FLOW OF CURRENT. THIS IS CALLED *ELECTRIC RESISTANCE*.












OHM'S LAW AND METHODS OF CONNECTING ELECTRICAL COMPONENTS


WHEN THERE IS A BIG DIFFERENCE IN WATER PRESSURE, THE FORCE OF FLOWING WATER INCREASES AND

CAUSES A WATER WHEEL TO ROTATE VIGOROUSLY. WITH ELECTRICITY, THE HIGHER THE VOLTAGE, THE MORE CURRENT WILL FLOW.



IF THIS WATER WHEEL WERE LARGER, THE WATER FLOW WOULD SLOW DOWN, AND THE QUANTITY OF WATER THAT FLOWS PER SECOND WOULD BE REDUCED, RIGHT?


FLIP



OKAY, RIGHT.


FLIP

IN THE SAME WAY, THE LARGER THE ELECTRIC RESISTANCE, THE MORE THE CURRENT FLOW IS REDUCED.






I GET IT!

ELECTRICITY FLOWS ACCORDING TO A CERTAIN LAW.




WHAT LAW IS THAT?




SERIES AND PARALLEL CONNECTIONS

THERE ARE TWO MAIN CONNECTION METHODS USED IN ELECTRIC CIRCUITS.

WHAT ARE THEY?



SERIES CONNECTIONS FOR CONNECTING TWO RESISTANCES IN A LINE...




AND PARALLEL CONNECTIONS FOR CONNECTING TWO RESISTANCES SIDE BY SIDE.

HOW DO THEY DIFFER?

THE WAY IN WHICH CURRENT FLOWS AND THE WAY IN WHICH VOLTAGE IS APPLIED BOTH DIFFER.


SERIES CONNECTION



CURRENT OF POWER SUPPLY = CURRENT OF RESISTANCE 1 = CURRENT OF RESISTANCE 2





VOLTAGE OF POWER SUPPLY = VOLTAGE OF RESISTANCE 1 + VOLTAGE OF RESISTANCE 2

PARALLEL CONNECTION



CURRENT OF POWER SUPPLY = CURRENT OF RESISTANCE 1 + CURRENT OF RESISTANCE 2

VOLTAGE OF POWER SUPPLY = VOLTAGE OF RESISTANCE 1 = VOLTAGE OF RESISTANCE 2



IF WE REPRESENT IT IN A FORMULA,
IT LOOKS LIKE THIS:

$$\text{EFFECTIVE RESISTANCE} = \frac{1}{\frac{1}{R_1} + \frac{1}{R_2}} = \frac{R_1 \times R_2}{R_1 + R_2}$$

(PRODUCT OVER SUM)




GRRRR!
IT CERTAINLY
IS COMPLICATED.

WELL, LET'S GET A
FEEL FOR IT FIRST,
OKAY?

HUFF

OKAY...

IF TWO IDENTICAL
LIGHT BULBS ARE
CONNECTED IN SERIES,
THE RESISTANCE VALUE
IS DOUBLED, RIGHT?



1 BULB



BRIGHT —

2 BULBS



DIM —

IN THIS CASE, SINCE THE
CURRENT IS HALVED, THE
BRIGHTNESS OF EACH BULB IS
DIMMER THAN WHEN JUST ONE
BULB IS CONNECTED.

TO GET THE SAME
BRIGHTNESS IN BOTH
BULBS AS WHEN ONE
BULB IS CONNECTED,
WE MUST DOUBLE
THE VOLTAGE.

CLICK

IF WE CONNECT THE BULBS IN PARALLEL, THE SAME VOLTAGE IS APPLIED TO EACH BULB, AND SINCE THE SAME CURRENT IS FLOWING, THE BRIGHTNESS DOES NOT CHANGE. HOWEVER, THE TOTAL CURRENT IS DOUBLED.

EVEN THOUGH THE CURRENT BRANCHES, THE CURRENT FLOWING TO A SINGLE BULB IS THE SAME.

IN OTHER WORDS, WE NEED A POWER SUPPLY THAT MAKES TWICE AS MUCH CURRENT FLOW.

THESE CONNECTION METHODS EACH HAVE SPECIAL CHARACTERISTICS, DON'T THEY?

A HOUSEHOLD ELECTRIC APPLIANCE ALSO ACTS AS A RESISTANCE. WE CAN CONNECT MANY OF THEM IN PARALLEL TO A 120V POWER SUPPLY FROM THE BREAKER.

THEREFORE, A VOLTAGE OF 120V IS APPLIED TO EVERY ELECTRIC APPLIANCE.


I GET IT!

ALL 120V

ELECTRIC CIRCUITS AND CURRENT

The electrical parts that make up a flashlight are the batteries, a miniature light bulb, and a switch. A battery has the ability to make electrical current flow, so it is called the *power supply*. The light bulb is a part that emits light when current flows through it. The switch is a part that lets electricity flow or stops it according to the opening and closing of a contact.

When the switch is closed, current leaves the positive pole of the battery, passes through the light bulb and switch, and returns to the negative pole. The path through which current flows in this way is called an *electric circuit*, which always has a closed form (a *closed circuit*).




Electric circuit of a flashlight

GRAPHICAL SYMBOLS

A basic electric circuit consists of three elements: power supply voltage, current, and electric resistance. These elements are connected by electric wires.

The power supply voltage that does the work of making current flow is called the *electromotive force*. The element that converts electric energy to light or heat when current flows is called the *load* (loads can also convert electrical energy into other things like sound or motion). The load has a property that hinders the flow of current, and this is called *electric resistance* or simply *resistance*. Resistance is represented by the symbol R and measured in *ohms* (Ω), which come from the name of the German physicist Georg Simon Ohm.

Creating a realistic drawing of an electric circuit takes time and effort. Therefore, *graphical symbols* are generally used to draw a representation. Using standard graphical symbols enables anyone to easily understand a circuit diagram that was drawn by someone else.




Electric circuit and graphical symbols

Appliances that use electric resistance include electric heaters and toasters. The electric heating element used in these appliances is the part that converts electrical energy to heat energy when current flows through the electric resistance. Note that the electric wire used in these appliances also has electric resistance; although it is only a small amount of resistance, when current flows through the electric wire, heat is generated.

DIRECT CURRENT CIRCUIT AND ALTERNATING CURRENT CIRCUIT


The direction the current flows in a circuit that has a battery as the power supply is fixed, and the size of the current is also constant. When the direction of the flow of current and the size of the current are fixed, we call the electricity *direct current (DC)*. A circuit in which direct current flows is called a *direct current (DC) circuit*. A power supply that sends out direct current, such as a battery, is called a *DC power supply*. A size D or size AA battery has a DC 1.5V power supply voltage.



Direct current and alternating current

On the other hand, the direction of flow and size of the current sent from the electric power company to a home changes cyclically. This kind of electricity is called *alternating current (AC)*, and a circuit in which alternating current flows is called an *alternating current (AC) circuit*. The direction that this electricity flows changes 50 or 60 times per second, and its size also varies cyclically with time. The number of waves repeated in one second is called the *frequency*, which is represented by f and measured in *hertz (Hz)*.

The size of AC voltage at any given time is called the *instantaneous voltage*, and the largest value among the instantaneous voltages is called the *peak voltage*. The size of the AC voltage that will perform the same amount of work as a DC voltage is called the *effective voltage*. The AC voltage that comes to an electric outlet in a home is generally 120V in the United States, but this is the effective voltage. The peak voltage is approximately 170V.




Alternating current value

OHM'S LAW

The current that flows in a circuit is directly proportional to the voltage and inversely proportional to the resistance. This relationship is called *Ohm's law* and can be expressed in a formula as $I = V / R$. This is the most important and basic property in electric circuits.

For example, if a voltage of 120V is applied to a resistance of 120Ω , the current will be $I = V / R = 120 / 120$, and 1A of current will flow. Whenever you know two values among the current, voltage, and resistance in a circuit, you can use Ohm's law to calculate the value you don't know.



Ohm's law

RESISTIVITY AND CONDUCTIVITY

Electric wire has a very low resistance and is used to connect circuit elements. When a small amount of current flows through wire, we can consider its resistance negligible. If a larger amount of current flows through a wire than can do so safely, heat will be generated.


Resistance (R) is a measure indicating the difficulty of the flow of current. The resistance (measured in ohms) of a conductor with length L meters and cross-sectional area A square meters can be represented by $R = \rho \times L / A$.

Resistivity measures how much a material opposes the flow of current and can be used to determine a wire's resistance. Resistivity, represented by the symbol ρ , is a material-specific resistance value and is measured in *ohm meters* (Ωm). From this equation it is apparent that for the same material, the size of the resistance is directly proportional to the length and inversely proportional to the cross-sectional area.

RESISTIVITY (IN Ωm) OF VARIOUS METALS AT ROOM TEMPERATURE (68°F)

Gold	2.22×10^{-8}
Silver	1.59×10^{-8}
Copper	1.69×10^{-8}
Aluminum	2.27×10^{-8}
Nichrome	107.5×10^{-8}

Conductance (G), in contrast to resistance, is a measure indicating the ease of the flow of current and is measured in *siemens* (S). Conductivity, represented by the symbol σ , is the reciprocal of resistivity, and it is measured in *siemens per meter* (S/m). (The siemens, named for German inventor Ernst Werner von Siemens, is an inverse ohm; it is also sometimes called a *mho* and can be represented by the symbol $\mathcal{O}$ or Ω^{-1}).



Resistivity and conductivity


EFFECTIVE RESISTANCE

There are two basic methods of connecting electrical components. Let's look at them both with respect to resistance. When there are multiple resistances in a circuit, we can consider them as a single *effective resistance*.

The method of connecting resistances in a line is called a *series connection*. We calculate the value of the effective resistance in a series connection by totaling the individual resistance values.


$$\text{Effective resistance} = R_0 = R_1 + R_2 + \dots + R_n$$

In this connection, the size of the current that flows in each resistance is the same. The power supply voltage is voltage divided by each resistance.



Series connection and effective resistance

If two light bulbs of the same size are connected in series to a power supply, the current will be halved, and the brightness of each bulb will be dimmer than it was when just a single bulb was connected, because the effective resistance is doubled. At this time, the voltage at both sides of each light bulb will be half the value of the power supply voltage.



Series connection of light bulbs


The other basic method of connecting resistances is called a *parallel connection*. At this time, the value of the effective resistance can be obtained by calculating the reciprocal of the sum of the reciprocals of each resistance.

$$\text{Effective resistance} = R_0 = \frac{1}{\frac{1}{R_1} + \frac{1}{R_2} + \dots + \frac{1}{R_n}}$$

The total resistance when two resistances are connected in parallel can be obtained as follows.


$$\text{Effective resistance} = R_0 = \frac{R_1 \times R_2}{R_1 + R_2} \quad (\text{Product over sum})$$

In a parallel circuit, the voltage applied to each resistance is the same, because the current branches and flows to each resistance.



Parallel connection and effective resistance

If two light bulbs of the same size are connected in parallel to a power supply, the brightness of each bulb is the same as it is when there is only one bulb. Since the current flowing to each bulb is the same as the current flowing when only one bulb is connected, the total current is doubled.



Series connection of light bulbs

The 120V electric appliances that we use in our homes are connected in parallel to a 120V power supply. If we increase the number of electric appliances connected to the power supply, the total current flowing also increases.



3

HOW DOES ELECTRICITY WORK?




WHY DOES ELECTRICITY
PRODUCE HEAT?

SO, HOW'S
IT GOING?

ARE THE
LESSONS
GOING WELL?



THEY'RE
GREAT!



SPENDING SOME TIME
ON EARTH SEEMS LIKE
IT WAS THE PERFECT
THING FOR YOU NOW,
DOESN'T IT?




YES! BY
PROPERLY
REVIEWING THE
BASICS HERE,
I WILL REGAIN
MY HONOR IN
ELECTOPIA!



REGAIN?

HIKARU SENSEI
AND I HAVE REALLY
HIT IT OFF!





YOU NEVER
HAD ANY
HONOR IN
THE FIRST
PLACE!



JEEZ! THAT
WAS ROUGH.










ELECTRICITY AND JOULE HEAT











HOW IS HEAT GENERATED BY CURRENT?














* SEE PAGE 61.













THIS PHENOMENON, IN WHICH THE TEMPERATURE OF A SUBSTANCE INCREASES AND THERMAL ENERGY IS EMITTED AS ELECTROMAGNETIC WAVES, IS CALLED *THERMAL EMISSION*. IT IS THE PRINCIPLE OF LIGHT EMISSION IN LIGHT BULBS.

EMISSION OF LIGHT AND HEAT



IT'S ALSO WHY IT GETS PRETTY WARM NEAR A LIGHT BULB!



THERMAL EMISSION PRODUCES RED LIGHT AT A LOW TEMPERATURE, WHICH CHANGES TO BLUISH WHITE LIGHT AS THE TEMPERATURE RISES.


THAT ALSO HAPPENS AS A DESK LAMP GETS BRIGHTER.



ACTUALLY, LIGHT EMISSION DUE TO THERMAL EMISSION MOSTLY ENDS UP BECOMING HEAT, SO IT'S INEFFICIENT TO USE IT AS LIGHT.



IS THAT RIGHT?

CLICK












ONE TYPE OF LIGHT EMISSION THAT ISN'T THERMAL EMISSION IS CALLED *LUMINESCENCE*. IT IS USED IN FLUORESCENT LIGHTS.




WOW!








CURRENT AND MAGNETIC FIELDS















FLEMING'S LEFT-HAND RULE (FOR DC MOTORS)





FLEMING'S RIGHT-HAND RULE (FOR GENERATORS)

FLEMING ALSO HAS A
RIGHT-HAND RULE!

WHAT DOES THAT
RULE SAY?

IF A CONDUCTOR
MOVES BETWEEN THE
POLES OF A MAGNET,
THE CONDUCTOR
CROSSES THROUGH A
MAGNETIC FIELD.

MOTION OF THE
CONDUCTOR

CONDUCTOR

MAGNETIC
FIELD

OKAY...

AN ACTION THAT CAUSES
ELECTRICITY TO FLOW, WHICH IS
CALLED THE *ELECTROMOTIVE
FORCE*, IS GENERATED IN THE
CONDUCTOR AT THIS TIME, AND
CURRENT FLOWS.

MAGNETIC
FIELD

N-TO-S MAGNETIC
FIELD POINTS IN
THIS DIRECTION




CONDUCTOR
MOVES IN THIS
DIRECTION

CURRENT
MOVES IN THIS
DIRECTION





MOTION

CURRENT

THE FLOW OF THAT CURRENT
IS IN THE DIRECTION OF THE
MIDDLE FINGER OF THE RIGHT HAND,
THE DIRECTION OF THE MAGNETIC FIELD
IS THE DIRECTION OF THE INDEX FINGER,
AND THE DIRECTION OF MOVEMENT OF
THE ELECTRIC WIRE IS THE DIRECTION
OF THE THUMB.








JOULE HEAT

Heat that is produced when current flows through an electric resistance is called *joule heat*. For example, the amount of heat produced when current I flows through resistance R for t seconds can be obtained by calculating $I^2 \times R \times t$. The amount of heat is represented by the symbol Q and is measured in *joules* (J), which are named after the English physicist James Prescott Joule. One joule corresponds to the electric power consumption of 1Ws (watt second)—and one joule is equivalent to a $\text{kg} \times \text{m}^2 / \text{s}^2$. The amount of heat required to raise 1 gram of pure water from 14.5°C to 15.5°C at 1 atmosphere of pressure is approximately 4.2J, and this is equivalent to 1 *calorie* (*cal*).



Resistance and joule heat


THERMAL VIBRATION

What is heat? The atoms that make up a substance are always vibrating, and this is called *thermal vibration*. The magnitude of the thermal vibration in a substance is directly related to the magnitude of the temperature of that substance—this thermal vibration of atoms is the true nature of heat.

If the atoms in a substance are not vibrating, that substance will have no temperature—that temperature is called *absolute zero*, which is equal to -273.15°C .

Even when copper wire, which is used for electric wire because of its low resistance, is at normal temperatures, the vibration of the copper atoms resists the movement of electrons, creating additional heat and additional resistance.


However, if the temperature of a material drops to near absolute zero, the vibrations of the atoms become very small. In such a state, electrons can travel much more easily—in other words, the material's resistance decreases. In some materials, such as aluminum, if the temperature becomes low enough, the electrons can move without



Thermal vibration and temperature


being obstructed by the atoms at all! When a material's resistance becomes zero, we call the phenomenon *superconductivity*.

Many metals are found to naturally superconduct when they are cold enough, but most need to be near absolute zero. However, since it is extremely difficult to actually lower a substance's temperature near absolute zero, research is being conducted on superconductivity phenomena that occur at temperatures much higher than absolute zero, a field called *high-temperature superconductors*. Someday, materials like these may be used to send electricity to homes everywhere without current loss due to joule heating.



Superconductivity and current


In wires at normal temperatures, electrons will violently collide with other atoms, which creates even more thermal vibrations—that is, more heat. As a wire heats up, its resistance increases. Conversely, as its temperature decreases, electric resistance decreases.



Collisions with electrons and generation of heat

ELECTROMAGNETIC WAVES

When current flows through a resistance and the temperature rises, heat is generated. At first, infrared rays that are invisible to the naked eye are emitted. *Infrared rays*, which are also called *heat rays*, are a type of *electromagnetic wave*—a wave that has thermal energy. Electromagnetic waves (in order of decreasing wavelength) include radio waves, infrared rays, visible light, ultraviolet rays, and X rays, among others. Radio waves are used for TV or radio broadcasting and communication for ships. The color of visible light varies with the wavelength—red light has the longest wavelength, and violet light has the shortest.




Wavelength and classification of electromagnetic waves

After infrared rays are emitted from a substance, visible light will be emitted if the temperature continues to rise. This phenomenon in which thermal energy is emitted as electromagnetic waves as the temperature of a substance increases is called *thermal emission*. This is the principle of light emission in light bulbs. Thermal emission produces red light at a low temperature, which changes to bluish white light as the temperature rises.

Light emission due to thermal emission mostly ends up becoming heat, so it is inefficient to use it as light. Light emission in which the emitter does not need to be heated is called *luminescence*; it is the principle used in fluorescent lights. In a fluorescent light, electrons that escape from the filament collide with mercury vapor inside the fluorescent tube; the ultraviolet rays that are generated at that time excite the fluorescent substance on the inner surface of the fluorescent tube and become visible light. The light emission of a fluorescent light is very efficient—for the same electric power consumption, it emits more than four times the light that a regular light bulb emits.

Light-emitting phenomena include thermal emission and luminescence, as shown here.




Light emission of a light bulb and a fluorescent tube

ELECTRICITY AND MAGNETISM

If iron filings are sprinkled on a sheet of paper placed over a bar magnet, a pattern of lines is produced. These lines originate from the north (N) pole and lead toward the south (S) pole; they are called a *magnetic field*.


Magnetic fields are also generated when current flows. This phenomenon is extremely important when using electricity, and many common electrical appliances make use of it.

When current flows in an electric wire, a magnetic field with a circular pattern is generated around that wire. This is called *Ampère's law*. The magnitude of this magnetic field varies according to the strength of the current; if the direction of the current changes, the direction of the magnetic field also changes.




A magnet and magnetic fields

If current of the same magnitude flows in the same direction in two electric wires placed side by side, the magnetic fields generated in each wire are combined to generate a magnetic field of twice the current around both conductors. At this time, a force of attraction is generated between the two electric wires. If current is flowing in opposite directions in two wires, a force of repulsion is generated between the wires. In this case, the magnetic fields around the wires negate each other and become smaller.



Ampère's law




Forces generated when current flows in two conductors


The additive property of magnetic fields also holds true for more than two wires (for example, a coil). In this way, a large magnetic field can be generated.

FLEMING'S LEFT-HAND RULE AND MOTORS

If current flows in a conductor that is within a magnetic field, an *electromagnetic force* is generated on the conductor. *Fleming's left-hand rule* indicates an easy-to-remember relationship among the directions of the magnetic field, the current, and the movement of the conductor. This rule says that when you extend the thumb, index finger, and middle finger of your left hand so they are mutually perpendicular, the index finger points in the direction of the magnetic field, the middle finger points in the direction of the current, and the thumb points in the direction that the conductor moves (the direction of the electro-magnetic force). The name of this rule comes from the name of the English electrical engineer John Ambrose Fleming who defined it. You can determine the direction of rotation of a motor by using Fleming's left-hand rule.




Fleming's left-hand rule




Motor rotation

FLEMING'S RIGHT-HAND RULE AND ELECTRIC GENERATORS

You can determine the direction of the electromotive force created by an electric generator by using *Fleming's right-hand rule*. When a conductor moves between the poles of a magnet, the conductor crosses a magnetic field facing from the north (N) pole to the south (S) pole of the magnet; electromotive force is thus generated in the conductor, and current flows. *Fleming's right-hand rule* indicates an easy-to-remember relationship among the directions of the magnetic field, the movement of the conductor, and the current. When you extend the thumb, index finger, and middle finger of your right hand so they are mutually perpendicular, the index finger points in the direction of the magnetic field, the thumb points in the direction that the conductor moves, and the middle finger points in the direction of the current.



Fleming's right-hand rule




Electricity generated by a generator

You must apply a force to keep the loop spinning within the magnetic field. This could be the force from falling water, like in a hydroelectric generator, or the force of pressurized steam, like in a coal power plant.

But why do Fleming's hand laws work? We can better understand why generators and motors work by understanding how magnetism and electricity are related.

ELECTRICITY AND COILS

An electric wire wound in loops is called a *coil*. If current flows in a coil, a magnetic field is generated that goes through the inside of the coil. If an iron core is inserted in the coil, the magnetic field is concentrated in the iron, and it becomes a strong *electromagnet*. The strength of an electromagnet is proportional to the product of the current and the number of loops in the coil; if the direction of the current is reversed, the polarity of the electromagnet is also reversed. If the current is stopped, the magnetic force of the electromagnet disappears.




Magnetic field created by a coil of electric wire

You can use your right hand to find the orientation of the magnetic field induced by a coil. Just curl your fingers in the direction the current flows in the coil, and your thumb will point towards the N pole of the induced magnetic field.

COILS AND ELECTROMAGNETIC INDUCTION

When a bar magnet moves within a coil, current flows in that coil, which creates a magnetic field in order to oppose the change in magnetism. If the direction of the bar magnet's movement changes, the direction of the current in the wire also changes. This phenomenon is called *electromagnetic induction*, and the electricity that is generated during this process is called *induced electromotive force*. The current generated is called *induced current*.

Lenz's law, discovered by the Russian physicist Heinrich Friedrich Emil Lenz, states that the current due to electromagnetic induction flows in a direction such that the magnetic field produced by that current obstructs the motion of the magnet.




Electromagnetic induction

COILS AND INDUCTANCE

If a coil is connected to a battery and current begins flowing, the magnetic field generated becomes larger, and the coil becomes an electromagnet. At this time, an induced electromotive force is generated on the coil itself due to the varying magnetic fields. This is called *self-induction* or simply *inductance*.

When the current to the coil is cut off, the magnetic field begins to disappear, and an induced electromotive force is generated in the direction that obstructs the flow of current in the coil. This is called a *counter-electromotive force*. The counter-electromotive force can be easily verified. When a battery is connected to a coil and current flows, a magnetic field is generated. When the current is constant, no counter-electromotive force is generated, but when the battery is detached and the current is cut off, the magnetic field that was being generated becomes smaller. At this time, voltage due to the counter-electromotive force appears at both ends of the coil.



Self-induction of a coil

COILS AND ALTERNATING CURRENT


The magnitude of alternating current is always changing. If alternating current flows in a coil, an induced electromotive force is generated in the coil in the direction that obstructs the flow of the current, and current flows so that it lags behind the power supply voltage variation by one-fourth of a cycle. This is called the *lagging current*, and it flows in an electrical device such as a motor with a coil. This temporal lag is called a *phase difference*. The coil acts like a resistance to the current as described above. This is called *inductive reactance*, and its magnitude is proportional to the frequency of the alternating current.

Electric power consumption is represented by the product of voltage and current, and when the voltage and current waves match with respect to time, 100 percent work is done—in other words, “the power factor is 100 percent.” If the current lags, the power factor will be less than 100 percent, and the circuit is said to have a “low power factor.”

If the power factor is low, the electric power that is input from the power supply will not do 100 percent work, so a power supply having a correspondingly larger capacity is required. The ratio of the consumed power to the input power is the *power factor*.

$$\text{Power factor} = \frac{\text{Consumed power}}{\text{Input power}}$$

A low power factor means that some current returns to the power supply without doing work.




Lagging current flowing in a coil

COILS AND TRANSFORMERS

If an AC power supply is connected to coil 1, a magnetic field is generated. When this magnetic field varies within coil 2, an induced electromotive force is generated in coil 2. This phenomenon is called *mutual induction*. A *transformer* is an electrical device that uses this phenomenon to change voltage.

If two coils are wrapped around an iron core, and an AC power supply is connected to coil 1, a magnetic field is generated and passes through the inside of the iron core. Since coil 2 has been wrapped around the same iron core, the magnetic field varies inside coil 2, and an induced electromotive force is generated in coil 2.

The power supply side of a transformer is called the *primary side*, and the load side is called the *secondary side*. The voltage generated on the secondary side is determined by the ratio of the number of turns (n_1) of the primary coil and the number of turns (n_2) of the secondary coil. For example, if the number of turns of the secondary coil is twice that of the primary coil, twice the voltage is generated on the secondary side. The current that flows



Mutual induction in a transformer

in the secondary coil at this time will be half the current that flows in the primary coil. The equation that describes this relationship is:

$$V_1 I_1 = V_2 I_2$$


The ratio of the primary voltage (V_1) and secondary voltage (V_2) is called the *transformation ratio*, and the product of the primary voltage and the current will be equal to the product of the secondary voltage and the current. In other words, a transformer only changes voltage—it does not change the magnitude of the electric power.

CAPACITORS

When an insulator is sandwiched between two metal plates and a battery is connected, electrons move from the negative pole of the battery to the bottom metal plate to charge it. Since the electrons in the top metal plate move to the positive pole of the battery, the top metal plate is positively charged. At this time, charge is stored on the metal plates. An object that stores charge in this way is called a *capacitor*.

Current flows from the instant the battery is connected, but eventually the electrons will stop moving, as charge builds on the capacitor. In other words, if a DC power supply is connected to a capacitor, current flows only at first and then stops because of the gap in the circuit. If the battery is detached in this state, the charge remains stored on the capacitor. If the battery is then connected in the reverse direction, the charge that had been stored discharges, and the capacitor is charged in the opposite direction.

The ability of the capacitor to store charge in this way is called *capacitance*; its magnitude is directly proportional to the area of the metal plate and inversely proportional to the distance between the metal plates. Capacitance is measured in *farads* (F).



Charge stored on a capacitor

CAPACITORS AND ALTERNATING CURRENT

If AC voltage is applied to a capacitor, a charged current flows until the power supply voltage reaches its maximum (starting from 0V). The current is zero at the power supply's peak voltage. When the power supply voltage decreases from its peak voltage, discharging begins, and the discharge current reaches its maximum when the power supply voltage is 0V.


At this time, the polarity of the power supply voltage changes, and a current flows again. Charging stops when the power supply voltage reaches its peak voltage for the opposite polarity, and then discharging occurs again.

If a capacitor is connected to an AC power supply, the variation of the current is one-fourth of a cycle ahead of the variation of the power supply voltage; this current is called *leading current*.

A capacitor works like resistance to alternating current. This is called *capacitive reactance*, and its magnitude is inversely proportional to the frequency.

If an AC circuit has a coil, the current lags, and the power factor decreases. If a capacitor is connected to that circuit, the current leads, and the power factor increases.

In an AC circuit, capacitors and coils act like resistance, and are called *impedance*.



Leading current flowing in a capacitor







4




HOW DO YOU CREATE ELECTRICITY?



GENERATORS









HOW DOES A POWER GENERATOR CREATE ELECTRICITY?

FIRST, LET'S TALK ABOUT ELECTRICITY CREATED BY AN ELECTRIC GENERATOR. THE OTHER DAY, WE TALKED ABOUT ELECTRICITY BEING CREATED ACCORDING TO FLEMING'S RIGHT-HAND RULE.







YEAH! IT'S THIS, RIGHT?





YES, BUT ACTUALLY, SINCE THE LOOP OF WIRE IS ROTATING WITHIN THE MAGNETIC FIELD, ELECTRICITY IS CREATED FOR WHICH BOTH THE MAGNITUDE AND DIRECTION OF FLOW VARY REPEATEDLY LIKE A WAVE.





THIS IS AC ELECTRICITY, RIGHT?



















BATTERIES AND OTHER SOURCES OF ELECTRICITY









CHEMICAL CELLS










ALTHOUGH HYDROGEN IONS H^+ AND SULFURIC ACID IONS SO_4^{2-} EXIST IN THE DILUTED SULFURIC ACID...



IF ZINC IONS ARE PRODUCED THERE, THE HYDROGEN, WHICH HAS A WEAKER IONIZATION TENDENCY THAN ZINC...

...UNITES WITH THE ELECTRONS THAT MOVED TO THE COPPER PLATE AND BECOMES HYDROGEN GAS.



...AND ELECTRONS MOVE FROM THE ZINC PLATE TO THE COPPER PLATE...











THE HYDROGEN GAS IS PRODUCED FROM THE COPPER PLATE!



ELECTRICAL ENERGY IS PRODUCED.





TAP TAP

I SEE!










ALTHOUGH THE MANGANESE DRY CELL AND THE ALKALINE DRY CELL LOOK ALIKE ON THE OUTSIDE, THEIR INSIDES ARE RATHER DIFFERENT, AREN'T THEY?



SINCE THE ALKALINE DRY CELL IS STRUCTURED TO CONTAIN A LOT OF MANGANESE DIOXIDE AND ZINC, IT PROVIDES GREATER CURRENT AND HAS A LONGER LIFETIME.

MANGANESE

ALKALINE

THEREFORE, AN ALKALINE DRY CELL IS SUITABLE FOR THE POWER SUPPLY OF A DEVICE THAT REQUIRES A LARGE CURRENT, SUCH AS A MOTOR.

I SEE.

MANGANESE DRY CELL

IF IT'S GIVEN A REST, ITS VOLTAGE IS RESTORED.

CLOCK FLASHLIGHT

REMOTE CONTROL

ALKALINE DRY CELL





ELECTRIC POWER FLOWS CONTINUOUSLY.

MOTOR DIGITAL CAMERA



PORTABLE RADIO

IF YOU UNDERSTAND THE CHARACTERISTICS OF DRY CELLS, YOU'LL BE ABLE TO USE EACH TYPE IN EXACTLY THE RIGHT WAY.

THAT'S TRUE!




WHEN ELECTRICITY IS PASSED THROUGH IT, HYDROGEN AND OXYGEN ARE PRODUCED AT THE RESPECTIVE ELECTRODES, WHICH ARE PLATINUM OR ANOTHER NON-CORROSIVE METAL.



AQUEOUS SOLUTION OF SODIUM HYDROXIDE


INCIDENTALLY, IN ELECTROLYSIS, THE ELECTRODE THAT THE POSITIVE SIDE OF THE POWER SUPPLY IS CONNECTED TO IS CALLED THE ANODE...




...AND THE ELECTRODE THAT THE NEGATIVE SIDE OF THE POWER SUPPLY IS CONNECTED TO IS CALLED THE CATHODE.






I SEE!

IF THE POWER SUPPLY IS REMOVED FROM THE ELECTROLYZED AQUEOUS SOLUTION...





...AND A LOAD IS CONNECTED...






ANODES AND CATHODES






MECHANISM OF A FUEL CELL




IF ONLY WATER IS EMITTED AFTER THE ELECTRICITY IS CREATED, IT ALSO SEEMS TO BE GOOD FOR THE ENVIRONMENT, RIGHT?

YUP.





CREATING YOUR OWN COIN BATTERY



ONCE WE KNOW ABOUT THE CHEMICAL REACTION THAT A BATTERY USES, IT'S SIMPLE TO CREATE ONE OF OUR OWN.

IS THAT RIGHT?

ALL WE NEED IS TWO TYPES OF METAL AND AN ELECTROLYTE. WE CAN EVEN USE COMMON ITEMS THAT ARE CLOSE AT HAND.



FOR EXAMPLE...

...ALL WE NEED IS THIS STUFF!

TABLE SALT

PENNY

WATER

TISSUE

ALUMINUM FOIL




WOW!

IF WE JUST USE A PENNY (COPPER) FOR THE POSITIVE POLE, A FOLDED PIECE OF ALUMINUM FOIL FOR THE NEGATIVE POLE, AND INSERT A TISSUE THAT WAS SOAKED IN SALT WATER AS THE ELECTROLYTE BETWEEN THEM, WE HAVE A BATTERY!



PENNY (+)




FOIL (-)

TISSUE SOAKED IN SALT WATER



THERMOPILES





THE GREATER THE TEMPERATURE DIFFERENCE BETWEEN THE JUNCTIONS, THE GREATER THE CURRENT THAT WILL FLOW. CURRENT WILL CONTINUE TO FLOW AS LONG AS THERE IS A TEMPERATURE DIFFERENCE.

LOW TEMPERATURE
LOWER

CURRENT

HIGH TEMPERATURE
HIGHER

AHA!

THE JUNCTIONS OF THESE TWO TYPES OF METALS ARE CALLED **THERMOCOUPLES**.

IF THIS IS COMBINED WITH AN AMMETER, IT CAN ALSO BE USED AS A THERMOMETER.

AN AMMETER MEASURES CURRENT IN A CIRCUIT.

COOL!

THAT'S BECAUSE WE CAN TELL THE TEMPERATURE APPLIED TO THE THERMOCOUPLE BY CHECKING THE AMOUNT OF CURRENT, RIGHT?

EXACTLY!

THERE IS ALSO A PHENOMENON THAT IS THE REVERSE OF THE SEEBECK EFFECT. IF A DC CURRENT IS CONNECTED TO THE THERMOCOUPLES AND CURRENT FLOWS, THE THERMOCOUPLE AT ONE SIDE WILL ABSORB HEAT AND THE OTHER ONE WILL GENERATE HEAT.




DC CURRENT




METAL A




ABSORB HEAT

METAL B

GENERATE HEAT









ELECTRICITY CREATED BY A POWER PLANT

In power plants, no matter what the source of motion, a turbine spins, which generates electricity in a generator.




Electricity created by a power plant

An electric generator creates electricity according to Fleming's right-hand rule. And since the conductor is rotating within the magnetic field, both the magnitude and direction of the electricity's flow vary repeatedly like a wave. The maximum voltage is generated when the loop of wire cuts through the magnetic field at a right angle, and the voltage is zero when the direction of the magnetic field and the direction of the loop's movement are the same.




Electricity generated in a conductor



Electricity created by an electric generator

The electricity that is created by this process is called *alternating current (AC)*. This is the electricity that comes from a household electric outlet. One wave is created by one rotation of the conductor within the magnetic field. If the conductor rotates 60 times per second, 60 waves are produced per second. This would be electricity with a frequency of 60 hertz (Hz).

The voltage of an ordinary household electric outlet is 120V AC. The *peak voltage* of the wave of this electricity is approximately 170V. The value of 120V represents the *effective voltage*, which is the value for which direct current (DC) electricity does the same work—in other words, the amount of heat generated when 120V AC is applied to a resistance is the same as the amount of heat generated when 120V DC is applied to the same resistance.




AC voltage and effective voltage

THERMAL POWER GENERATION

The types of thermal power generation that generate the most electrical power are steam generation, internal combustion generation, gas turbine generation, and combined cycle generation.

Steam generation burns fuel such as oil, coal, or liquefied natural gas (LNG) in a boiler to generate high-temperature, high-pressure steam. The force of that steam turns a turbine that is coupled with an electric generator to generate electricity.


The steam that was used to generate electricity is cooled in a device called a *condenser*; once it returns to liquid water, it is then sent to the boiler again.



Turbine and steam power generation

Internal combustion generation uses an internal combustion engine (like a diesel engine) to generate electricity.

Gas turbine generation uses a combustion gas such as kerosene or diesel oil to turn a gas turbine and create electricity.




Combined cycle generation

Combined cycle generation combines steam generation and gas turbine generation. Electricity is generated by a gas turbine, and then the heat of the exhaust gas is used to create steam to turn a steam turbine and generate more electricity; this is an efficient method of generating electricity.

NUCLEAR POWER GENERATION

Nuclear power generation uses the heat generated when the nuclear fission of uranium occurs in a nuclear reactor to create high-temperature, high-pressure steam, which turns a turbine and creates electricity. When a neutron collides with uranium-235, it decays to thorium-231; several neutrons as well as heat are emitted. The neutrons successively collide with other uranium-235 nuclei, causing *nuclear fission* to occur and generating a great deal of thermal energy.

Nuclear power generation uses this heat to create steam, which turns a turbine and generates electricity in a manner similar to thermal power generation. *Control rods*, which absorb neutrons, and a *moderator*, which reduces the speed of the neutrons, are used in the nuclear reactor to control nuclear fission and regulate the reactor's output.




The nuclear fission of uranium-235 leads to more neutrons, which may strike other U-235 atoms, causing a chain reaction.


There are various types of nuclear reactors. Currently, the type that is used most often is called a *light water reactor*, which uses light water (ordinary water) as a moderator and coolant. Light water reactors include boiling water reactors and pressurized water reactors.

A *boiling water reactor* sends steam that was generated in the reactor pressure vessel directly to the turbine; after it turns the turbine, the steam turns back into liquid water in a device called a condenser, and the water is reused. A *condenser* uses ocean water to cool the steam so it turns back into liquid water and can be reused.

A *pressurized water reactor* passes boiling water that was created in the reactor pressure vessel to the steam generator, where water from a separate system is changed to steam, which turns the turbine.



Boiling water reactor




Pressurized water reactor

HYDROELECTRIC POWER GENERATION

Hydroelectric power generation uses the potential energy of water to generate electricity. *Dam-type power generation* stores water at a high location and lets the water drop from there to turn a water turbine coupled with an electric generator to generate electricity.


Since it is easier to start and stop power generation and to increase or decrease the amount of power generated via hydroelectric power generation than it is to do so for thermal or nuclear power generation, hydroelectric power can be generated corresponding to varying power demands. Also, during periods of low power demand, a lift pump can be used to draw water up to the higher location to store it as potential energy.

For hydroelectric power generation to use the energy of water efficiently, several types of water turbines are used for different purposes according to the *head (height difference)* or amount of water.




Dam-type power plant

A *Francis turbine* is used for a large amount of running water and a medium to high head. This type of water turbine is used for approximately 70 percent of the hydroelectric power generation in Japan. The water is directed perpendicular to the main shaft from all directions, the blades inside the turbine change the water's direction to the axial direction, and the turbine is rotated by hydraulic power when the water is discharged.



Francis turbine


A *Pelton wheel* is a water turbine that rotates from the recoil that occurs when water sprayed from a nozzle hits a spoon-shaped bucket (blade). It is useful in locations that have a high head.



Pelton wheel

A *Kaplan turbine* is a water turbine that rotates because several propeller blades connected to a shaft adjust their angles according to variations in the amount of water flowing or the head. This kind of turbine is useful in locations having a low head. A type of Kaplan turbine that does not adjust the angle of the blades is called a *propeller turbine*.


Although hydroelectric power generation accounts for only 10 percent of Japan's power generation, it is a valuable method for a country with few resources.



Kaplan turbine

WIND POWER GENERATION

Wind power generation uses wind power to turn a turbine; the turbine in turn rotates an electric generator to create electricity.



Mechanism of wind power generation (propeller wind turbine)

There are various types of wind turbines for wind power generation. A *propeller wind turbine*, which uses wind power energy very efficiently, is common. When wind hits the turbine's blades, it creates rotational motion, and the rotation speed is increased by a gearbox to turn an electrical generator. An *anemoscope (wind vane)* and an *anemometer (wind gauge)* constantly measure the wind conditions, and the direction of the propeller and angle of the blades are adjusted to the optimum state to use the wind power most effectively.

Although the power supplied by wind power generation is greatly affected by variations in the direction and speed of the wind, and the noise that is generated when the wind turbine rotates can be a problem, this is a clean, environmentally friendly power generation method that requires no fuel and produces no exhaust gases.




5


HOW CAN YOU CONVENIENTLY USE
ELECTRICITY?




FORTUNATELY, HIKARU WAS ABLE TO REPAIR
YONOSUKE'S BREAKDOWN WITH THE
TECHNOLOGY AVAILABLE ON EARTH.













HE WORKED ON YONOSUKE EVERY NIGHT...










AND SEVERAL DAYS LATER...











WHAT ARE SEMICONDUCTORS?



WOW!




THERE ARE SO MANY THINGS FOR SALE HERE!

THERE ARE ALL KINDS OF ELECTRONIC DEVICES AND ELECTRONIC COMPONENTS!




SPY CAMERAS... WIRETAPS...?

UH, DON'T LOOK AT THAT STUFF! LET'S SEE WHAT'S OVER HERE...!



SEMICONDUCTOR DEVICES ARE AN IMPORTANT PART OF MANY ELECTRONIC DEVICES.




SEMI-WHO?



A SEMICONDUCTOR IS SOMETHING THAT HAS PROPERTIES IN BETWEEN THOSE OF A CONDUCTOR, THROUGH WHICH ELECTRICITY EASILY PASSES, AND AN INSULATOR, THROUGH WHICH ELECTRICITY HAS DIFFICULTY PASSING.

OH, OKAY!



SCRIBBLE, SCRIBBLE...



ELECTRICITY FLOWS EASILY


RESISTIVITY IN $\Omega\text{ m}$

ELECTRICITY HAS DIFFICULTY FLOWING



THE DISTRIBUTION OF RESISTIVITIES OF VARIOUS SUBSTANCES LOOKS LIKE THIS.

GOT IT!



IN PARTICULAR,
SEMICONDUCTORS
ARE SUBSTANCES
WHOSE ELECTRICAL
CHARACTERISTICS CHANGE
DUE TO THE EFFECTS
OF HEAT, LIGHT, OR
ELECTRICITY.


THEY
SOUND
MYSTERIOUS!

SEMICONDUCTORS
MAY CONTAIN
SUBSTANCES SUCH
AS SILICON OR
GERMANIUM.

CHEMICAL SYMBOL

Ge **Si**
GERMANIUM SILICON

DIODES



TRANSISTORS

COMPONENTS SUCH AS
DIODES OR TRANSISTORS,
WHICH ARE CREATED USING
SEMICONDUCTORS, ARE
CALLED SEMICONDUCTOR
DEVICES.

WHEN YOU PUT IT
THAT WAY, IT'S EASY
TO UNDERSTAND!

Ge

Si

SILICON OR
GERMANIUM ARE
ELEMENTS, BUT...

GALLIUM + ARSENIC
=
GALLIUM ARSENIDE

...A SEMICONDUCTOR
THAT IS MADE UP
OF TWO OR MORE
ELEMENTS SUCH AS
GALLIUM ARSENIDE IS
CALLED A COMPOUND
SEMICONDUCTOR.

BOINK

Ga

As

THAT MAKES
SENSE!

THERE ARE ALSO CASES IN WHICH A SMALL AMOUNT OF AN IMPURITY IS MIXED WITH THE SILICON OR GERMANIUM.

THIS PROCESS IS CALLED *DOPING*, AND THE RESULT IS CALLED AN **EXTRINSIC SEMICONDUCTOR**.

A SEMICONDUCTOR WITH NO IMPURITY MIXED IN IS CALLED AN **INTRINSIC SEMICONDUCTOR**.

THERE SURE ARE A LOT OF TYPES OF SEMICONDUCTORS!

THE RAW MATERIAL MOST OFTEN USED IN SEMICONDUCTORS IS SILICON.

SILICON IS AN ELEMENT REPRESENTED BY THE SYMBOL **Si**.

Si
SILICON

I SEE!

NORMALLY, SILICON IS FOUND IN A SUBSTANCE CALLED *SILICON DIOXIDE*, WHICH IS A REFINED PRODUCT OFTEN USED AS THE RAW MATERIAL FOR SEMICONDUCTOR DEVICES.


THE PURITY OF THIS REFINED SILICON IS 99.999999999 PERCENT, WHICH IS SOMETIMES REFERRED TO AS **ELEVEN-NINE**.

THIS IS EXTREMELY CLOSE TO 100 PERCENT!!!


9×11
99.999999999%

ONE, TWO, THREE...

A SILICON ATOM HAS FOUR VALENCE ELECTRONS IN ITS OUTERMOST SHELL.



THESE ATOMS JOINTLY CONTRIBUTE FOUR ELECTRONS TO FORM A FIRM, REGULAR CRYSTAL.




*WELL-BUILT

IT'S LIKE THEY'RE HOLDING HANDS! LIKE THIS!

SQUEEZE

YEAH...UH... LIKE THAT.

A SILICON CRYSTAL DOES NOT HAVE ANY ELECTRONS THAT CAN FREELY MOVE AROUND, SO ELECTRICITY WILL HARDLY PASS THROUGH IT.












THAT'S BECAUSE THE VALENCE ELECTRONS OF THE SILICON ATOMS ARE HOLDING HANDS!




ELECTRICITY

SLAP





THAT'S RIGHT!






















DIODES AND TRANSISTORS



























THE PROPERTY THAT ALLOWS CURRENT TO FLOW ONLY IN ONE DIRECTION IN THIS WAY IS CALLED RECTIFICATION.





DIODES THAT EMIT LIGHT









TWO TYPES OF TRANSISTORS ARE NPN AND PNP TRANSISTORS.




THEY HAVE THREE ELECTRODES REFERRED TO AS B (BASE), C (COLLECTOR), AND E (EMITTER).

THEY HAVE ONE MORE ELECTRODE THAN A DIODE!








IF AN NPN TRANSISTOR IS CONNECTED LIKE THIS...




...THE ELECTRONS IN THE COLLECTOR ARE DRAWN TO THE POSITIVE POLE WHERE THEY ACCUMULATE.










ON THE OTHER HAND, THE ELECTRONS IN THE EMITTER ARE PUSHED TO THE NEGATIVE POLE AND ACCUMULATE NEAR THE BASE-EMITTER JUNCTION INTERFACE.



































DIODES

When a single diode is connected to an AC power supply, current flows to the load for only one direction of the AC power supply due to rectification. Rectification that only allows a half-cycle of the alternating current to flow is called *half-wave rectification*, and the current that flows to the load in this process flows in only one direction, just like a direct current power supply. But since only a half-cycle of the AC waveform flows, this kind of rectification is inefficient.




Half-wave rectification

When four diodes are arranged in a bridge configuration and an AC power supply is connected, the current of the entire cycle becomes positive and flows to the load. This kind of rectification is called *full-wave rectification*, and diodes that are connected in this way are called a *diode bridge*. Full-wave rectification enables current from the entire cycle of the AC power supply to be used as direct current.




Full-wave rectification

Although this kind of full-wave rectification is more efficient than half-wave rectification, the waveform exhibits large pulsations. However, if an electrolytic capacitor is connected to the output, the charging and discharging of the capacitor can change the pulsations in the waveform into a flat, smooth direct current. A capacitor that is used to change a pulsating flow to a flat waveform in this way is called a *smoothing capacitor*.



Smoothing capacitor

If a reverse-direction voltage is applied to a *Zener diode* (or *constant-voltage diode*) and the value of the voltage is steadily increased, current will flow once a certain voltage is reached. This phenomenon is called *breakdown*, and when the circuit voltage rises more than necessary, current can flow from the cathode to the anode to suppress the rise in voltage. This characteristic of a Zener diode is used in a constant voltage circuit that maintains a fixed voltage.




Characteristics of a Zener diode

If an ordinary diode is used as a Zener diode, it will be damaged because breakdown and the Zener current will be concentrated locally within the diode.

TRANSISTORS


A *transistor* is a semiconductor device that amplifies signals or acts as a switch by controlling the current or the voltage that is applied to an electrode.

When a large amount of electric power is controlled by a transistor that is used as a switch, the transistor is called a *power transistor*. Generally, an NPN-type transistor is used in this way.



Transistor symbols

A switch that uses a transistor has no contact that will wear out, reducing the occurrence of failures, allowing it to be turned on and off rapidly, and allowing users to finely tune control of the device.




Transistor that does the work of a contact

FIELD-EFFECT TRANSISTOR

A transistor in which the collector current is controlled by the change of current that is input to the base is called a *bipolar transistor* (*junction transistor*). In contrast, a transistor that is controlled by changing the voltage that is input, rather than the current, is called a *field-effect transistor* (FET).

The merits of a field-effect transistor are that power consumption is low and response speed is extremely fast because current does not flow to the input. A field-effect transistor has three terminals that are referred to as *G* (*gate*), *D* (*drain*), and *S* (*source*), which correspond to the base, collector, and emitter of a bipolar transistor, respectively. A field-effect transistor controls the drain current according to changes in the voltage that is input to the gate.




Field-effect transistor (N-channel type)

An *integrated circuit (IC)* is a device in which an extremely large number of elements such as transistors or resistors are placed on one component; ICs are used in more complex electronic devices such as TVs and computers. An amplifier called a *MOSFET (metal-oxide semiconductor field-effect transistor)*, in which the input gate is insulated by a thin film of silicon dioxide, is used in ICs.


CONVERTERS AND INVERTERS

A device that uses a diode to convert alternating current to direct current is called a *converter*, and a device that converts direct current to alternating current is called an *inverter*.



Converter and inverter

An inverter uses a semiconductor switching device such as a transistor to do the work of a switch. Single-phase alternating current can be produced by connecting four semiconductor switching devices and alternately turning on and off A, D, B, and C, as shown in the next figure. The frequency of the single-phase alternating current can be changed at will by varying the switching speed of the semiconductor switching devices.



Single-phase alternating current created by an inverter

The rotational speed of an *induction motor* is directly proportional to the power supply frequency. If the supply frequency is constant, the rotational speed will also be constant.

For an air conditioner to cool the air, a motor must turn a compressor to compress the refrigerant gas. If the rotational speed of the motor is constant, a large capacity will be output even when a small capacity is required, and electrical power will be wasted.

Therefore, energy-saving operation with no waste can be achieved by using an inverter to create alternating current with the frequency required to continuously vary the rotational speed of the motor according to the required capacity.

A DC motor that is rotated by a DC power supply is used in the newest inverter air conditioners. In order to vary the rotational speed of the DC motor, the voltage must also vary, so a semiconductor switching device is used for this purpose.

In addition to air conditioners, inverters are also widely used in other familiar electrical appliances such as lighting or refrigerators and even in railroad cars.

SENSORS

Various sensors are used in electrical appliances in place of the perceptions of our eyes or skin. For example, an electric thermostat uses a temperature sensor to detect the temperature and turn a heater on and off, so we need not repeatedly turn the switch on and off ourselves.


Since sensors convert physical information such as light or heat to electrical information, if they are incorporated into an electric circuit, they can allow an electrical appliance to operate automatically. There are also sensors that can detect magnetism, which cannot be perceived by humans, or infrared rays, which cannot be seen by the naked eye.

TEMPERATURE SENSORS

A *temperature sensor* is a device that opens or closes a contact or varies electrical resistance according to the temperature it detects. Temperature sensors include contact-type sensors, which perceive the temperature by directly touching the substance whose


temperature they are trying to measure, and non-contact-type sensors, which perceive emitted thermal energy without directly touching the substance whose temperature they are trying to measure.

There are many types of contact-type temperature sensors such as thermostats, thermistors, and thermocouples. Non-contact-type temperature sensors include infrared sensors.



Classification of temperature sensors

A bi-metal thermostat is the simplest temperature sensor. It uses a bi-metal strip consisting of two types of metal with different thermal expansion rates, which curves in response to a temperature change. Although a thermostat is used in an appliance like an electric blanket, since the heater is turned on and off directly by a contact, the thermostat can only control large temperature fluctuations. A temperature sensor using a bi-metal strip is also used for the overcurrent action of a circuit breaker.




Temperature control by a bi-metal thermostat

A *thermistor* is a temperature sensor whose electrical resistance varies according to a temperature change. Generally speaking, electrical resistance also varies with temperature

for any metal. However, thermistors' resistance changes significantly, even in response to a small temperature change. Since a large current does not flow directly to a thermistor, it is used in combination with an electrical circuit to control temperature.

Thermistors are classified into *positive temperature coefficient (PTC) thermistors*, those whose resistance value rises when the temperature rises, and *negative temperature coefficient (NTC) thermistors*, those whose resistance value falls when the temperature rises.

The newest air conditioners and electric refrigerators use thermistors for temperature sensors, combined with electrical circuits that use semiconductor devices to enable temperature control to be finely tuned.




Temperature characteristics of thermistors

OPTICAL SENSORS

An *optical sensor* perceives light like our eyes do. These sensors are frequently used to automatically turn on street lights when it gets dark, and they function as the receiver of an infrared remote controller on an electrical appliance.


An optical sensor converts light energy to electrical signals. The phenomenon in which a substance such as a metal absorbs light energy and emits electrons as a result is called the *photoelectric effect*.



Photoelectric effect

The phenomenon that describes how voltage appears at the junction of a semiconductor due to the photoelectric effect is called the *photovoltaic effect*. Optical sensors that use the photovoltaic effect include *photodiodes* and *phototransistors*. A solar cell that is used for photovoltaic power generation also uses the photovoltaic effect to create electricity.

A *solar cell* generates an electromotive force when light energy strikes the p-n junction surface, causing the electrons and holes to move to the negative and positive poles, respectively. When a load is connected to a solar cell, current flows.




Photovoltaic effect of a solar cell

The effect in which a carrier of electricity such as an electron is generated by the photoelectric effect, thus causing the internal resistance value of a substance to change, is called *photoconductivity*. A *cadmium sulphide (CdS) cell* is a solar cell that functions using photoconductivity.


A *photodiode* is a semiconductor device in which current flows from the cathode to the anode due to the photovoltaic effect when light or infrared rays are received. The current that flows at this time varies according to the intensity of the light, and the photodiode measures this current.

The current when the light is received is extremely small. It is generally used by applying a reverse-bias voltage.




Photodiode

A photodiode combined with a transistor is called a *phototransistor*. Although a phototransistor has no base, a collector current flows when light is received in a manner similar to how base current flows in a transistor. The current in the collector varies according to the intensity of the light.




Phototransistor

An optical sensor like a phototransistor can be used to determine the position or existence of a target object without touching it.






Photoelectric effect and optical sensors





Optical sensors are widely used for various purposes such as detecting brightness and turning on or dimming lights; an optical sensor can also be used in a security system as a photoelectric eye that detects the changes in light—that is, movement.



Uses of optical sensor

WITHOUT REREKO AROUND,
I RETURNED TO REGULAR
LIFE—SPENDING ALL MY
TIME IN THE LAB.





LABORATORY

SWOOSH!

I WONDER IF MY
DATA IS OKAY...!?

HIKARU
SENSEI!?

AHHHH!

ZZZUUUH?

RE...REREKO!?

YEP, IT'S ME!!
IT'S NICE TO SEE
YOU AGAIN!

WHY ARE YOU BACK?
MORE MAKEUP
CLASSES!?

NOPE!
THANKS TO YOU,
I HAD NO PROBLEM
GRADUATING.



INDEX

A

absolute zero, 87, 88, 104–105
AC. *See* alternating current (AC)
active material, 132
air conditioners, 192
alkaline dry cell batteries, 125, 133–134
alternating current (AC), 64–66, 75–76, 113–116, 121, 123, 149, 173, 189–190
 circuits, 75–76
 power supply, 114, 121, 123, 186
amber, 25
ammeter, 143
Ampère, André Marie, 45
amperes/amps (A), 16, 45, 68
Ampère's law, 96, 107–108
anemometer/anemoscope, 154
anions, 127
anodes, 136–139, 169, 171, 193
appliances, electrical, 19, 24, 45, 46, 56–58, 71–72, 96, 123, 190
atomic numbers, 34
atomic structures, 34–35
atoms, 26–28, 34–35, 47, 127, 165
attraction, force of, 25, 49–50, 97, 108

B

base-collector junction, 179
base current, 178, 179–181, 182
base-emitter junction, 177–178
batteries, 45, 59–60
 AA, 46–47, 74
 chemical reactions and, 120
 coils and, 112
 coin, 140–141, 174
 creating your own, 140–141
 dry cell, 125, 130, 131, 132–134, 171–172, 178

 in flashlights, 59, 73
 lithium, 125
 as power supplies, 63–64, 124–125
 solar, 125
 supply voltage, 46–47
 types of, 125
 voltage of stacked, 47
bi-metal thermostats, 191
bipolar transistors, 188
boilers, 147
boiling water reactors, 151–152
boron, 167, 168
breakdowns, 187
breakers, 19, 21–23
 circuit, 19, 21
C
cadmium sulphide (CdS) cells, 193
calories, 85, 86, 104
capacitance, 115
capacitive reactance, 116
capacitors, 115–116, 187
cathodes, 136–139, 169, 171, 193
cations, 127, 128
CdS (cadmium sulphide cells), 193
cells, 124–132
 cadmium sulphide, 193
 chemical, 124–132
 fuel, 124–125, 135–138
 galvanic, 126, 130
 physical, 124–125
 solar, 125, 193
 voltaic, 125
 water, 135–137
charges, 29
 attraction and repulsion, 25, 49–50, 97, 108
 electrical discharges, 31–33, 51
 measuring, 49
 negative/positive, 29, 30–33, 36–39, 42, 47–48, 50–52
 polarity of, 41
 stored on capacitors, 115

chemical cells/reactions, 124–132, 137, 138
circuits
 alternating current, 75–76
 in appliances, 56–58
 breakers, 19, 21
 closed, 61, 73
 connection methods used in, 69–72, 78–80
 creating your own, 141, 142
 diodes in, 171
 direct current, 64, 74–75
 drawings of, 73, 74
 electrical parts of, 61–66, 73
 in flashlights, 58–61, 73
 integrated (ICs), 183
 parallel, 79
closed current, 61
coal (as fuel), 147, 149
coils, 108, 111–115
coin batteries, 140–141, 174
collector current, 179–181
collector-emitter current, 182, 188
collectors, 177–180, 182
combined cycle generation, 149, 150–151
compasses, 95
compound semiconductors, 163
condensers, 149, 151
conductance (*G*), 77
conductivity, 34–35, 77, 135, 166, 168
 photoconductivity, 193, 195
 superconductivity, 88, 105
conductors, 30–31, 98–100, 108–110, 127, 148, 161, 162
connections, electrical, 69–72, 78–80
constant-voltage diodes, 187
consumed power, 17–18
consumer electric products, 20–24. *See also* electrical appliances

contactless switches, 181–182
 contacts, switch, 60, 61, 73, 188
 contact-type sensors, 191
 control rods, 151
 converters, 189–190
 copper
 atoms, 35
 plate, 126, 127, 128, 130, 140
 wires, 31, 104, 128
 copy machines, 43
 cotton, 41–42, 51
 Coulomb, Charles Augustine, 49
 Coulomb's force, 29, 43, 49–50
 coulombs (Q), 45, 49–50, 104
 counter-electromotive force, 112
 current (*I*)
 alternating, 64–66, 75–76,
 113–116, 121, 123, 149,
 173, 189–190
 base, 178, 179–181, 182
 closed, 61
 collector, 179–181
 collector-emitter, 182, 188
 defined, 16, 45, 51, 128
 direct, 64, 66, 74–75, 123,
 149, 173, 189–190
 direction of, 33, 51–52, 63–66,
 75, 96–97, 98–101
 drain, 189
 fixed, 63, 74
 flow of, 15–17, 20–24, 58,
 61, 63–68, 73–78, 96,
 108–109, 128
 forward direction, 187
 induced, 111
 lagging, 113
 leading, 116
 limiters, 21
 measuring, 16, 143
 rated, 23
 size of, 52
 speed of, 53
 temperature differences,
 142–143
 water, 181

D

dam-type power generation,
 152–153
 DC. *See* direct current (DC)
 depolarizers, 131
 digital cameras, 175
 diodes, 163, 169–171, 173, 177,
 183, 186–188, 189
 bridges, 186
 constant-voltage, 187
 light-emitting, 141, 174–175
 photodiodes, 193–194
 Zener, 187–188
 direct current (DC), 64, 66, 74–75,
 123, 149, 173, 189–190
 circuits, 64, 74–75
 power supply, 74
 direction, current, 33, 51–52,
 63–66, 75, 96–97, 98–101
 discharges, electrical, 31–33, 51
 doping, 164
 drain, 189
 current, 189
 dry cell batteries, 125, 130, 131,
 132–134, 171–172, 178

E

effective resistance, 69–72, 78–80
 effective voltage, 75–76, 123, 149
 electric
 current. *See* current
 generators, 101, 110,
 120–123, 147–149,
 152–154
 heaters, 62, 74
 outlets, 23–24, 63–64,
 123, 149
 power, 17–18, 19, 45, 46
 resistance. *See* resistance (*R*)
 shocks, 40, 66
 wires, 74, 77, 88, 96, 107,
 108, 148. *See also* coils
 electrical
 appliances, 19, 24, 45, 46,
 56–58, 71–72, 96, 123, 190

 charges. *See* charges
 connections, 69–72, 78–80
 discharges, 31–33, 51
 potential, 46–47
 electricity, nature of, 25–29
 electrochemical reactions, 132
 electrodes, 127, 136, 169, 177
 electrolytes, 126, 130, 132, 140
 electromagnetic
 force, 109, 111
 induction, 111–112
 waves, 91, 106–107
 electromotive force, 61, 73,
 100, 110, 111, 112,
 122, 130
 electrons, 26–29, 34–35, 47–48
 in chemical reactions, 128–129,
 137, 138
 collisions of, 89–90, 93, 105
 free, 27–28, 35, 47–48, 166,
 167, 170, 171
 holes, 167, 170, 174, 177–178
 movement and electric charges,
 49, 51–53
 single, 48
 speed of, 53
 valence, 34–35, 48,
 165–166, 167
 electron shells, 34–35, 47–48, 165
 electrostatic force, 29, 43, 49–50
 electrostatic induction, 40, 50
 emitter, 177–180, 182
 energy
 defined, 46
 heat, 61, 62
 light, 61, 62
 measuring, 46
 solar, 124–125
 thermal, 106, 124
 environmentally friendly
 power, 154
 escaped electrons. *See* free
 electrons
 Europe, voltage in, 45
 extrinsic semiconductors, 164, 168

F

farads, 115
field-effect transistor (FET), 188-189
fixed current, 63, 74
flashlights, 58-61, 73
Fleming, John Ambrose, 109
Fleming's left-hand rule, 98-99, 109
Fleming's right-hand rule, 100-101, 110, 121, 148
flow, current, 15-17, 20-24, 58, 61, 67-68, 73-78, 96, 108-109, 128
fluorescent lights, 92-93, 106-107
force of attraction, 25, 49-50, 97, 108
force of repulsion, 49-50, 97
forward bias voltage, 173, 174
forward direction current, 187
Francis turbine, 153
free electrons, 27-28, 35, 47-48, 166, 167, 170, 171
frequency, 65, 75, 122
frictional electricity, 38, 49. *See also* static electricity
fuel (oil, coal, and gas), 147, 149, 150
fuel cells, 124-125, 135-138
fuel reformers, 139
full-wave rectification, 186-187
fuses, 19

G

gallium arsenide, 163
galvanic cells, 126, 130
gamma rays, 91
gas (as fuel), 147, 149, 150
gas turbine generation, 149, 150
gate, 189
generators, 101, 110, 120-123, 147-149, 152-154
geomagnetism, 95
germanium, 163-164
giga-, 46
glass, 41-42, 51
graphical symbols, 73-74

H

hair, 41-42, 51
half-wave rectification, 186-187
heat energy, 61, 62
heaters, electric, 62, 74
heat generation, 85-93, 104-105, 123, 143-144
heat rays. *See* infrared rays
hertz (Hz), 65, 75, 122, 149
high potential electricity flow, 16, 46-47
high-temperature resistance, 89
high-temperature superconductors, 105
holes, 167, 170, 174, 177-178
home distribution boards, 20-21
hydroelectric generator, 110, 152-154
power generation, 120, 147
hydrogen gas, 129, 130, 131
ions, 129, 137, 138, 139
Hz (hertz), 65, 75, 122, 149

I

ICs (integrated circuits), 183
impedance, 116
induced current, 111
induced electromotive force, 111, 114
inductance, 112
induction
electromagnetic, 111-112
electrostatic, 40, 50
motors, 190
mutual, 114
inductive reactance, 113
infrared rays, 90-91, 106
innermost shells, 47
instantaneous voltage, 75-76
insulators, 30, 32, 161, 162
integrated circuits (ICs), 183
intensity of electricity, 45
internal combustion generation, 149, 150
International System of Units (SI units), 46

intrinsic semiconductors, 164
inverse ohms, 77
inverters, 189-190
ionization, 129
ions, 127, 129

J

Japan, 45, 65, 153, 154
Joule, James Prescott, 104
joule heat, 86, 104
joules (J), 45, 46, 104
junction transistors, 188

K

Kaplan turbine, 154
kilo-, 46
kilowatt hours (kWh), 18-19, 46

L

lagging current, 113
leading current, 116
LED (light-emitting diode), 141, 174-175
Lenz, Heinrich Freidrich Emil, 111
Lenz's law, 111
light bulbs, 59, 60-62, 71-72, 73
light emission, 92-93, 106-107
series connection of, 79, 80
light emission, 91-93, 106-107, 174-175
light-emitting diode (LED), 141, 174-175
light energy, 61, 62
light water reactors, 151
lighting, electric, 175, 190
lightning, 32-33, 51, 198
lights, fluorescent, 92-93, 106-107
liquefied natural gas (LNG), 149
lithium batteries, 125
LNG (liquefied natural gas), 149
loads, 61, 62, 73, 136, 182, 187
loops, 99, 121, 122, 148
low potential electricity flow, 16, 46-47
low power factor, 113

low-temperature resistance,
89, 104
luminescence, 90–93,
106–107, 175

M

magnetic fields, 94–98, 100,
107–109, 111, 114,
121, 148
magnetism, 94–97, 107–108,
110, 111
magnets, 94, 107, 110, 111
manganese dioxide, 132, 134
manganese dry cell batteries, 125,
131, 132, 134
mega-, 46
metal-oxide semiconductor
field-effect transistors
(MOSFETs), 189
metals
aluminum, 88–89, 140
bi-metal thermostats, 191
copper, 34–35, 41–42,
47–48, 51
properties of, 35
steel, 41–42, 51
mho. *See* siemens per meter (S/m)
micro-, 46
microwaves, 91
milli-, 46
mobile phones, 175
moderators, 151
MOSFETs (metal-oxide semi-
conductor field-effect
transistors), 189
motion, 73
motors, 98–99, 101, 109,
110, 190
mutual induction, 114

N

negative electrical properties,
27–28, 31, 166
negative ions, 127
negative poles, 46–47, 73, 132,
140, 171, 177–178
negative temperature coefficient
(NTC) thermistors, 192

neutrons, 27, 47–48
newtons (N), 49
non-contact type sensors, 191
north magnetic pole, 94–95, 99,
100–101, 107, 110, 111,
121–122
NPN-type transistors,
177–178, 188
NTC (negative temperature
coefficient) thermistors, 192
N-type semiconductors, 166,
169–171, 172
nuclear
fission, 147, 151
power generation, 120, 147,
151–152
reactors, 147, 151
nucleus, 26–27, 34–35, 47–48
nylon, 41–42, 51

O

Ohm, Georg Simon, 73
ohms (Ω), 62, 73, 77, 162
Ohm's law, 67–68, 76
oil (as fuel), 147, 149, 150
optical sensors, 192–195
outermost shells, 35, 47, 48, 165
outlets, 23–24, 63–64, 123, 149
oxidizing agents, 131

P

paper, 41–42, 51
parallel circuits, 79
parallel connections, 69–72, 79–80
peak voltage, 75–76, 123, 149
Peltier device/effect, 144
Pelton wheel, 153
phase difference, 113
phosphorus, 168
photoconductivity, 193, 195
photodiodes, 193–194
photoelectric effect, 192, 195
photoemission effect, 195
phototransistors, 193, 195–196
photovoltaic effect, 193
physical cells, 124–125
pico-, 46
plugs, 24, 63–64

P-N junction, 169, 170, 174, 193
PNP-type transistors, 177–178,
181, 188
polarization, 41, 131
polyester, 41–42, 51
polyethylene, 41–42, 51
positive electrical properties,
27–28, 168
positive ions, 127
positive poles, 46–47, 61, 73, 132,
171, 177–178, 179
positive temperature coefficient
(PTC) thermistors, 192
potential barriers, 170–171
potential difference, 15–16
power generation
dam-type, 152–153
hydroelectric, 120, 147
nuclear, 120, 147, 151–152
thermal, 120, 147, 149–152
wind, 154
power lines, 20
power (P), 17–18, 19, 45, 46
power plants, 20, 120, 147–154
power supplies, 63–64, 72, 182
alternating current, 114, 121,
123, 186
batteries, 63–64, 124–125
direct current, 74
voltage, 60–61, 62, 73–74,
78, 115
power transistors, 188
pressurized water reactors,
151–152
primary cells, 124–125
primary sides, 114
primary voltage, 115
propeller wind turbine, 154
protons, 27, 29, 34, 47–48
PTC (positive temperature
coefficient) thermistors, 192
P-type semiconductors, 168,
169–171, 172
PVC (vinyl), 37, 39, 41–42, 51

R

radio waves, 91, 106
rated current, 23

reactors
 boiling water, 151–152
 light water, 151
 nuclear, 147, 151
 pressurized water, 151–152
 rectification, 170, 173
 red light, 91, 106
 reduction–oxidation (redox), 132
 refrigerators, 190, 192
 repulsion, force of, 49–50, 97
 resistance (R), 61–62, 67–74, 76, 77, 79–80, 85, 88–89, 104, 105, 182
 resistances, connecting, 69–72, 78–80
 resistivity (ρ), 77, 162
 resistors, 183
 reverse–bias voltage, 171, 193
 reverse–direction voltage, 187
 reverse electromotive force, 130
 rice cookers, 22
 rubber, 41–42, 51

S

safety breakers, 21–23
 secondary cells, 124–125
 secondary sides, 114
 Seebeck effect, 142–144
 self–inductance, 112
 semiconductors, 30, 163, 166–171, 172
 devices, 160–164, 161, 163, 169, 176, 183, 188–189
 sensors
 contact–type, 191
 defined, 190
 non–contact–type, 191
 optical, 192–195
 temperature, 190–192
 series connections, 69–72, 78–80
 shocks, electric, 40, 66
 Siemens, Ernst Werner von, 77
 siemens per meter (S/m), 77
 silicon, 163–166, 167
 crystals, 165, 168
 dioxide, 164
 silk, 41–42, 51
 single electrons, 48

single–phase alternating current, 189–190
 SI prefixes and units, 46
 size, current, 52
 smoothing capacitors, 187
 sodium hydroxide, 135–136
 solar
 batteries, 125
 cells, 125, 193
 energy, 124–125
 sound, 73
 source, 189
 south magnetic pole, 94–95, 99, 100–101, 107, 110, 121–122
 speed, current/electron, 53
 static electricity, 25, 29, 32, 36–40, 49–53
 electrostatic force, 29, 43, 49–50
 triboelectric series, 51–53
 uses of, 43–44
 steam engines, 45
 steam generation, 149, 150
 steel, 41–42, 51
 sulfuric acid, 127, 129
 sum of reciprocals, 70–71
 superconductivity, 88, 105
 supply voltage, 46–47
 switches, 59, 60–61, 73, 74, 176, 181–182
 symbols
 amperes/amps (A), 16, 45, 68
 charges (Q), 49
 conductance (G), 77
 coulombs (C), 45, 49–50, 104
 current (I), 16, 143
 farads (F), 115
 giga– (G), 46
 hertz (Hz), 65, 75, 122, 149
 joules (J), 45, 46, 104
 kilo– (k), 46
 kilowatt hours (kWh), 18–19, 46
 micro– (μ), 46
 milli– (m), 46
 mega– (M), 46
 newtons (N), 49

ohms (Ω), 68, 73, 77, 162
 pico– (p), 46
 power (P), 17–18, 19, 45, 46
 resistance (R).
 See resistance (R)
 resistivity (ρ), 77, 162
 siemens per meter (S/m), 77
 tera– (T), 46
 time (t), 52
 units and SI prefixes, 46
 voltage (V). See voltage (V)
 volts (V), 15, 17–18, 45, 68
 watt seconds (Ws), 46, 104
 watts (W), 17, 45

T

tags, consumer electronic, 45
 tea kettles, 14, 18, 22
 temperature sensors, 190–192
 tera–, 46
 Thales (philosopher), 25
 thermal
 emission, 90–93, 106
 energy, 106, 124
 power generation, 120, 147, 149–152, 149–154
 vibration, 87–90, 104–105
 thermistors, 191–192
 thermocouples, 143
 thermoelectric phenomena, 144
 thermopiles, 125, 141–143
 thermostats, 191
 time (t), 52
 toasters, 74
 traffic signals, 175
 transformation ratio, 115
 transformers, 20, 114–115
 stations, 20
 transistors, 163, 176–183, 183, 188–189
 amplification, 181
 bipolar, 188
 field–effect, 188–189
 junction, 188
 MOSFET, 189
 phototransistors, 193, 195–196
 PNP–type, 177–178, 181, 188
 power, 188

triboelectricity, 38
triboelectric series, 40–43, 51–53
turbine engines, 147, 149,
152, 153

U

UHF waves, 91
ultraviolet rays, 91, 93, 106, 107
United States, voltage in, 45
utility pole transformers, 20

V

valence electrons, 34–35, 48,
165–166, 167
valence shells, 48
VHF waves, 91
vinyl (PVC), 37, 39, 41–42, 51
violet light, 91, 106
visible light, 91, 93, 106
Volta, Alessandro, 45, 126
voltage (V)
100V, 14, 45
120V, 22, 45, 72, 75, 76, 80,
123, 149
170V, 75, 76, 149
240V, 45
changes in, 20
defined, 15, 45, 46–47
effective, 75–76, 123, 149
in electrical appliances, 19,
24, 45, 46, 71–72, 96,
123, 190
forward bias, 173, 174
instantaneous, 75–76
international differences, 45
peak, 75–76, 123, 149
positive and negative poles,
46–47, 61, 73, 132, 171,
177–178, 179
potential and, 46–47
power supply, 60–61, 62,
73–74, 78, 115
reverse-bias, 171, 193

reverse-direction, 187
supply, 46–47
voltaic cells, 125
volts (V), 15, 17–18, 45, 68

W


water
cells, 135–137
current, 181
levels, 15–16
turbine, 147, 152, 153–154
wheels, 17, 59–60
Watt, James, 45
watt seconds (Ws), 46, 104
watts (W), 14, 17, 19, 45
waveforms, 187
wavelength, 91, 106
waves
electromagnetic, 91, 106–107
radio, 91, 106
UHF, 91
VHF, 91
wind power generation, 154
wires
coils, 108, 111–115
copper, 31, 104, 128
electric, 74, 77, 88, 96, 107,
108, 148
wood, 41–42, 51
wool, 41–42, 51

X

X rays, 91

Z

Zener diodes, 187–188
zinc
chloride, 132
ions, 129
plate, 126, 127, 128
powder, 133



ABOUT THE AUTHOR

Kazuhiro Fujitaki is a lecturer at the Tokyo Metropolitan Vocational Skills Development Center. He has written a number of books on electrical engineering and runs a website offering information about Japan's qualifying examinations for electrical technicians. The site (in Japanese) is at <http://www10.ocn.ne.jp/~denkou/>.

PROJECT TEAM FOR THE JAPANESE EDITION

Production: TREND-PRO Co., Ltd.

Founded in 1988, TREND-PRO produces newspaper and magazine advertisements incorporating manga for a wide range of clients from government agencies to major corporations and associations. Currently, TREND-PRO is actively participating in advertisement and publishing projects using digital content. Some results of past creations are publicly available on the company's website, <http://www.ad-manga.com/>.

Ikeden Bldg., 3F, 2-12-5 Shinbashi, Minato-ku, Tokyo, Japan

Telephone: 03-3519-6769; Fax: 03-3519-6110

Scenario writer: re_akino

Artist: Matsuda






DTP: Mackey Soft Corporation

HOW THIS BOOK WAS MADE

The *Manga Guide* series is a co-publication of No Starch Press and Ohmsha, Ltd. of Tokyo, Japan, one of Japan's oldest and most respected scientific and technical book publishers. Each title in the best-selling *Manga Guide* series is the product of the combined work of a manga illustrator, scenario writer, and expert scientist or mathematician. Once each title is translated into English, we rewrite and edit the translation as necessary and have an expert review each volume. The result is the English version you hold in your hands.

MORE MANGA GUIDES


Find more *Manga Guides* at your favorite bookstore, and learn more about the series at <http://www.nostarch.com/manga>.



UPDATES

Visit http://www.nostarch.com/mg_electricity.htm for updates, errata, and other information.

ELECTRIFY YOUR LIFE!



REREKO IS JUST YOUR AVERAGE HIGH-SCHOOL GIRL FROM ELECTOPIA, THE LAND OF ELECTRICITY, BUT SHE'S TOTALLY FAILED HER FINAL ELECTRICITY EXAM! NOW SHE HAS TO GO TO SUMMER SCHOOL ON EARTH. AND THIS TIME, SHE **HAS** TO PASS.

LUCKILY, HER EVER-PATIENT TUTOR HIKARU IS THERE TO HELP. JOIN THEM IN THE ILLUSTRATED PAGES OF **THE MANGA GUIDE TO ELECTRICITY** AS REREKO EXAMINES EVERYDAY ELECTRICAL DEVICES LIKE FLASHLIGHTS, HEATERS, AND CIRCUIT BREAKERS, AND LEARNS THE MEANING OF ABSTRACT CONCEPTS LIKE VOLTAGE, POTENTIAL, CURRENT, RESISTANCE, CONDUCTIVITY, AND ELECTROSTATIC FORCE.

THE REAL-WORLD EXAMPLES THAT YOU'LL FIND IN **THE MANGA GUIDE TO ELECTRICITY** WILL TEACH YOU:

- ✧ WHAT ELECTRICITY IS, HOW IT WORKS, HOW IT'S CREATED, AND HOW IT CAN BE USED

- ✧ THE RELATIONSHIP BETWEEN VOLTAGE, CURRENT, AND RESISTANCE (OHM'S LAW)
- ✧ KEY ELECTRICAL CONCEPTS LIKE INDUCTANCE AND CAPACITANCE
- ✧ HOW COMPLICATED COMPONENTS LIKE TRANSFORMERS, SEMICONDUCTORS, DIODES, AND TRANSISTORS WORK
- ✧ HOW ELECTRICITY PRODUCES HEAT AND THE RELATIONSHIP BETWEEN CURRENT AND MAGNETIC FIELDS
- ✧ AND MUCH MORE!

IF THINKING ABOUT HOW ELECTRICITY WORKS REALLY FRIES YOUR BRAIN, LET **THE MANGA GUIDE TO ELECTRICITY** TEACH YOU ALL THINGS ELECTRICAL IN A SHOCKINGLY FUN WAY.



THE FINEST IN GEEK ENTERTAINMENT™
www.nostarch.com

\$19.95 (\$19.95 CDN)

SHELF IN: SCIENCE/ELECTRICITY

ISBN: 978-1-59327-197-8



9 781593 271978



5 1 9 9 5



6 89145 71972 7

FIND MORE MANGA GUIDES AT WWW.EDUMANGA.ME